GEOPHYSICS®

Approximate reflection coefficients for a thin VTI layer

Journal:	<i>Geophysics</i>
Manuscript ID	GEO-2016-0638.R3
Manuscript Type:	Technical Paper
Date Submitted by the Author:	22-Aug-2017
Complete List of Authors:	Hao, Qi; Norwegian University of Science and Technology, Petroleum Engineering and Applied Geophysics Stovas, Alexey; NTNU, Petroleum Engineering and Applied Geophysics
Keywords:	anisotropy, reflection, VTI, AVO/AVA, reflectivity
Area of Expertise:	Seismic Modeling and Wave Propagation, Anisotropy

SCHOLARONE™
Manuscripts

Approximate reflection coefficients for a thin VTI layer[‡]

Qi Hao¹ and Alexey Stovas²

Right Running Head: thin-layer reflection coefficients

¹Fomerly Norwegian University of Science and Technology (NTNU); presently King Abdullah University of Science and Technology (KAUST). Email: xqi.hao@gmail.com

²Norwegian University of Science and Technology (NTNU). Email: alexey.stovas@ntnu.no

Sep. 09th, 2017.

[‡]This paper is based on the expanded abstract that was presented at the 17th International Workshop on Seismic Anisotropy, September 18-23, 2016, in Austin, USA.

Abstract

We present an approximate method to derive simple expressions for the reflection coefficients of P- and SV-waves for a thin transversely isotropic layer with a vertical symmetry axis (VTI) embedded in a homogeneous VTI background. The layer thickness is assumed to be much smaller than the wavelengths of P- and SV-waves inside. The exact reflection and transmission coefficients are derived by the propagator matrix method. In the case of normal incidence, the exact reflection and transmission coefficients are expressed in terms of the impedances of vertically propagating P- and S-waves. For subcritical incidence, the approximate reflection coefficients are expressed in terms of the contrast in the VTI parameters between the layer and the background. Numerical examples are designed to analyze the reflection coefficients at normal and oblique incidence, and investigate the influence of transverse isotropy on the reflection coefficients. Despite giving numerical errors, the approximate formulae are sufficiently simple to qualitatively analyze the variation of the reflection coefficients with the angle of incidence.

Introduction

Reflection and transmission coefficients of plane waves are of importance in studying wave propagation. In reflection seismology, the main application of reflection coefficient studies is to analyze the amplitude variation with offset (AVO). Such parameters of reservoir rocks as fluid content, density and seismic wave velocities, may be determined from the variation of amplitude with incidence angle and azimuth.

For an interface separating two elastic half-spaces, the exact plane-wave reflection and transmission coefficients can be derived from the boundary condition that displacement and traction are continuous across the interface (Aki and Richards, 2002). Although it is straightforward to numerically calculate the reflection and transmission coefficients, the exact formulae suffer from high algebraic complexity. Simple approximate formulae help analyze the influence of the changes in the medium parameters across the interface on the reflection and transmission coefficients. For isotropic and anisotropic media, these approximate formulae can be found, for example, in Aki and Richards (2002), Thomsen (1993), Rüger (1996, 1997, 1998), Ursin and Haugen (1996), Vavryčuk and Pšenčík (1998), and Vavryčuk (1999). These approximations assume a weak contrast in density and velocity parameters, and weak anisotropy for a specific parameterization of the considered medium.

For horizontally layered elastic models, reflection and transmission of plane waves can be described by the propagator matrix method. For a single horizontal layer, the propagator matrix is constructed by considering the continuity of the particle displacement and traction at the top and bottom of the layer. For horizontally layered media, the whole propagator matrix linking the displacement and traction at the top to those at the bottom is represented by the product of the individual propagator matrices. The propagator matrix method to calculate reflection and transmission coefficients is systematically discussed in the monographs by Brekhovskikh (1980), Kennett (1983), Brekhovskikh and Godin (1989), Nayfeh (1995), and

Chapman (2004). The propagator matrix method for anisotropic media can be found in Fryer and Frazer (1984, 1987). More literature related to the propagator matrix method is referenced in these monographs.

In this paper, we study the reflection and transmission of plane waves from a thin homogeneous transversely isotropic layer with a vertical symmetry axis (VTI) embedded in a homogeneous VTI background (Figure 1). The term “thin” means that the thickness of the layer is much smaller than the wavelengths of waves propagating inside it. We consider the cases of P- and SV-wave incidence from the upper half-space. In addition to Voigt notation, Thomsen’s (1986) notation is used to describe a VTI medium. In Thomsen’s (1986) notation, v_{p0} and v_{s0} denote the velocities of the vertically propagating P and S-waves; ε and δ denote Thomsen (1986) anisotropy parameters. The density of medium is denoted by ρ . The stiffness coefficients can be explicitly expressed in terms of Thomsen parameters and density. For brevity, the term “plane” is omitted when describing P- and SV-waves throughout this paper.

The rest of the paper is organized as follows. First, we introduce the exact and approximate propagator matrices for a horizontal homogeneous VTI layer. Then, we present equations for reflection and transmission coefficients for a layer embedded in a homogeneous VTI background. Next, we introduce specific assumptions for the parameters of the layer and background, and derive relatively simple formulae for the reflection and transmission coefficients. Finally, we implement the proposed formulae to analyze the reflection and transmission coefficients for several VTI models.

Propagator matrix for a single VTI layer

The horizontal slowness component is preserved for the incident, reflected and transmitted waves in a horizontal layer (Figure 1). For all these waves, the unit polarization vector and the vertical slowness can be expressed in terms of the horizontal slowness component. The particle displacement and the traction are continuous across the upper and lower interfaces of the layer. The particle velocity, as the first-order derivative of particle displacement with respect to time, is also continuous across these interfaces. The particle velocity and the traction at the upper interface are linked to those at the lower interface by the propagator matrix B_{ij} (Appendix A),

$$\begin{pmatrix} v_x \\ v_z \\ \tau_{zz} \\ \tau_{zx} \end{pmatrix}_{z=0} = \begin{pmatrix} B_{11} & B_{12} & B_{13} & B_{14} \\ B_{21} & B_{22} & B_{23} & B_{24} \\ B_{31} & B_{32} & B_{33} & B_{34} \\ B_{41} & B_{42} & B_{43} & B_{44} \end{pmatrix} \begin{pmatrix} v_x \\ v_z \\ \tau_{zz} \\ \tau_{zx} \end{pmatrix}_{z=h}, \quad (1)$$

where B_{ij} are functions of the horizontal slowness component (explicit expressions for B_{ij} are given in equations A-9-A-18 in Appendix A), v_x and v_z are the horizontal and vertical components of the particle velocity, τ_{zx} and τ_{zz} denotes two components of a stress tensor, and $z = 0$ and $z = h$ correspond to the top and bottom of the layer.

Equation 1 plays the role of the boundary condition, which is used to link the incident and reflected waves in the upper half-space to the transmitted waves in the lower half-space. As illustrated in equations A-9-A-18 in Appendix A, the layer thickness h appears in B_{ij} in the dimensionless terms $hq_p\omega$ and $hq_s\omega$, where q_p and q_s denote the vertical slowness components of P- and SV-waves, respectively. If the layer thickness is much smaller than the wavelengths of P- and SV-waves propagating inside this layer, $hq_p\omega < hq_s\omega \ll 1$. We expand

equation 1 in $hq_p\omega$ and $hq_s\omega$, and then further expand q_p and q_s in the horizontal slowness p . The final expression is truncated after quadratic terms in h ,

$$\begin{pmatrix} B_{11} & B_{12} & B_{13} & B_{14} \\ B_{21} & B_{22} & B_{23} & B_{24} \\ B_{31} & B_{32} & B_{33} & B_{34} \\ B_{41} & B_{42} & B_{43} & B_{44} \end{pmatrix} \approx \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{pmatrix} + ih\omega \begin{pmatrix} 0 & B_{12}^{(1)} & 0 & B_{14}^{(1)} \\ B_{21}^{(1)} & 0 & B_{23}^{(1)} & 0 \\ 0 & B_{32}^{(1)} & 0 & B_{34}^{(1)} \\ B_{41}^{(1)} & 0 & B_{43}^{(1)} & 0 \end{pmatrix} - h^2\omega^2 \begin{pmatrix} B_{11}^{(2)} & 0 & B_{13}^{(2)} & 0 \\ 0 & B_{22}^{(2)} & 0 & B_{24}^{(2)} \\ B_{31}^{(2)} & 0 & B_{33}^{(2)} & 0 \\ 0 & B_{42}^{(2)} & 0 & B_{44}^{(2)} \end{pmatrix}, \quad (2)$$

where i denotes the imaginary unity; ω denotes the angular frequency; the nonzero elements $B_{ij}^{(1)}$ and $B_{ij}^{(2)}$ are given by equations A-21-A-30.

Exact reflection and transmission coefficients

As illustrated in Figure 1, we consider the reflection and transmission for P- and SV-waves separately incident upon the top of the layer. For the incident, reflected and transmitted P- and SV-waves, the horizontal component of the polarization unit vector is chosen to be always nonnegative, which agrees with the convention in Aki and Richards (2002).

P-wave incidence

Referring to Figure 1(a), the particle displacement functions of the incident, reflected and transmitted waves are defined as follows in terms of the horizontal slowness component.

The incident P-wave:

$$\mathbf{u}_{p\downarrow}^{(A-)} = (l_p, 0, m_p)^T \exp(-i\omega(t - px - q_p z)), \quad z \in (-\infty, 0), \quad (3)$$

The reflected P-wave:

$$\mathbf{u}_{p\uparrow}^{(A-)} = R_{pp}(l_p, 0, -m_p)^T \exp(-i\omega(t - px + q_p z)) , \quad z \in (-\infty, 0) , \quad (4)$$

The reflected SV-wave:

$$\mathbf{u}_{s\uparrow}^{(A-)} = R_{ps}(l_s, 0, m_s)^T \exp(-i\omega(t - px + q_s z)) , \quad z \in (-\infty, 0) , \quad (5)$$

The transmitted P-wave:

$$\mathbf{u}_{p\downarrow}^{(A+)} = T_{pp}(l_p, 0, m_p)^T \exp(-i\omega(t - px - q_p z)) , \quad z \in (h, +\infty) , \quad (6)$$

The transmitted SV-wave:

$$\mathbf{u}_{s\downarrow}^{(A+)} = T_{ps}(l_s, 0, -m_s)^T \exp(-i\omega(t - px - q_s z)) , \quad z \in (h, +\infty) , \quad (7)$$

where $\mathbf{u}$ denotes the vector of particle displacement; the superscripts “ $A-$ ” and “ $A+$ ” denote the upper ($A-$) and lower ($A+$) half-spaces relative to the layer; “ T ” denotes the transpose of a vector; the subscripts “ P ” and “ S ” denote P- and SV-waves; the arrows “ $\downarrow$ ” and “ $\uparrow$ ” in the subscripts denote up-going and down-going waves; l and m denote the absolute values of the horizontal and vertical components of the unit polarization vector of a considered wave; p denotes the horizontal slowness component; q_p and q_s denote the magnitudes of the vertical slowness components of P- and SV-waves. Explicit expressions for the polarization and slowness components can be found in Rüger (1996); R_{pp} and R_{ps} denote the P-P and P-SV reflection coefficients, and T_{pp} and T_{ps} denote the P-P and P-SV transmission coefficients, where the first subscript denotes incident wave, and the second subscript denotes reflected or transmitted wave; i is the imaginary unity; t and ω denote time and angular frequency, x and z denote the horizontal and vertical coordinates, and h denotes the layer thickness.

SV-wave incidence

As illustrated in Figure 1(b), we consider the SV-wave incident from the upper half-space. By analogy with the definitions in equations 3-7, the particle displacement functions of the incident, reflected and transmitted waves are found as follows.

The incident SV-wave:

$$\mathbf{u}_{s\downarrow}^{(A-)} = (l_s, 0, -m_s)^T \exp(-i\omega(t - px - q_s z)) , \quad z \in (-\infty, 0) , \quad (8)$$

The reflected P-wave:

$$\mathbf{u}_{p\uparrow}^{(A-)} = R_{sp}(l_p, 0, -m_p)^T \exp(-i\omega(t - px + q_p z)) , \quad z \in (-\infty, 0) , \quad (9)$$

The reflected SV-wave:

$$\mathbf{u}_{s\uparrow}^{(A-)} = R_{ss}(l_s, 0, m_s)^T \exp(-i\omega(t - px + q_s z)) , \quad z \in (-\infty, 0) , \quad (10)$$

The transmitted P-wave:

$$\mathbf{u}_{p\downarrow}^{(A+)} = T_{sp}(l_p, 0, m_p)^T \exp(-i\omega(t - px - q_p z)) , \quad z \in (h, +\infty) , \quad (11)$$

The transmitted SV-wave:

$$\mathbf{u}_{s\downarrow}^{(A+)} = T_{ss}(l_s, 0, -m_s)^T \exp(-i\omega(t - px - q_s z)) , \quad z \in (h, +\infty) , \quad (12)$$

where R_{sp} and R_{ss} denote the SV-P and SV-SV reflection coefficients, and T_{sp} and T_{ss} denote the corresponding transmission coefficients.

Equations for reflection and transmission coefficients

Using the displacement functions 3-7, we can obtain the particle velocity and traction in the upper and lower half-spaces. The substitution of the particle velocity and traction into

equation 1 allows us to derive a system of equations for the reflection and transmission coefficients for an incident P-wave. Similarly, we may also obtain another system of equations for the reflection and transmission coefficients in the case of SV-wave incidence. After combining the two systems, we obtain the following system of equations for the reflection and transmission coefficients:

$$\begin{pmatrix} l_p & l_s & E_1 & F_1 \\ -m_p & m_s & E_2 & F_2 \\ -c_p & -d_s & E_3 & F_3 \\ a_p & b_s & E_4 & F_4 \end{pmatrix} \begin{pmatrix} R_{PP} & R_{SP} \\ R_{PS} & R_{SS} \\ T_{PP} & T_{SP} \\ T_{PS} & T_{SS} \end{pmatrix} = \begin{pmatrix} -l_p & -l_s \\ -m_p & m_s \\ c_p & d_s \\ a_p & b_s \end{pmatrix}, \quad (13)$$

with

$$a_p = c_{55}(q_p l_p + p m_p), \quad (14)$$

$$b_s = c_{55}(q_s l_s - p m_s), \quad (15)$$

$$c_p = c_{13} p l_p + c_{33} q_p m_p, \quad (16)$$

$$d_s = c_{13} p l_s - c_{33} q_s m_s, \quad (17)$$

$$E_i = (B_{i4} a_p + B_{i3} c_p - B_{i1} l_p - B_{i2} m_p) \exp(i\omega q_p h), \quad (18)$$

$$F_i = (B_{i4} b_s + B_{i3} d_s - B_{i1} l_s + B_{i2} m_s) \exp(i\omega q_s h), \quad (19)$$

where B_{ij} correspond to the layer, while the other quantities including the stiffness coefficients c_{11} , c_{13} , c_{33} and c_{55} , the absolute values l and m of the components of the polarization vector, and the vertical slowness component q , correspond to the upper and lower half-spaces. Equation 13 describes the exact reflection and transmission coefficients for a homogeneous, horizontal VTI layer embedded in a homogeneous VTI background. In the case of normal incidence, the horizontal slowness vanishes, and the reflection and transmission coefficients are given by

$$R_{PP} = \frac{2r_{P0} \sin k_{P0}^{(M)}}{(1+r_{P0}^2) \sin k_{P0}^{(M)} + i(1-r_{P0}^2) \cos k_{P0}^{(M)}} , \quad (18)$$

$$R_{SS} = \frac{2r_{S0} \sin k_{S0}^{(M)}}{(1+r_{S0}^2) \sin k_{S0}^{(M)} + i(1-r_{S0}^2) \cos k_{S0}^{(M)}} , \quad (19)$$

$$T_{PP} = \frac{1-r_{P0}^2}{(1-r_{P0}^2) \cos k_{P0}^{(M)} - i(1+r_{P0}^2) \sin k_{P0}^{(M)}} , \quad (20)$$

$$T_{SS} = \frac{1-r_{S0}^2}{(1-r_{S0}^2) \cos k_{S0}^{(M)} - i(1+r_{S0}^2) \sin k_{S0}^{(M)}} , \quad (21)$$

with

$$r_{P0} = \frac{Z_{P0}^{(M)} - Z_{P0}^{(A)}}{Z_{P0}^{(M)} + Z_{P0}^{(A)}} , \quad r_{S0} = \frac{Z_{S0}^{(M)} - Z_{S0}^{(A)}}{Z_{S0}^{(M)} + Z_{S0}^{(A)}} , \quad (22)$$

$$k_{P0}^{(M)} = \frac{h\omega}{v_{P0}^{(M)}} , \quad k_{S0}^{(M)} = \frac{h\omega}{v_{S0}^{(M)}} , \quad (23)$$

where $Z_{P0} = \rho v_{P0}$ and $Z_{S0} = \rho v_{S0}$ denote the impedances of the vertically propagating P- and S-waves, and the superscripts “M” and “A” denote the layer and the background, respectively.

Approximate reflection and transmission coefficients

By analogy with the weak-contrast, weak-anisotropy approximations for the reflection and transmission coefficients at an interface separating two VTI half-spaces (Thomsen, 1993), we make the following assumptions to derive approximate formulae for the reflection coefficients from a thin layer.

First, we assume a small contrast in the elastic properties (including the density ρ , the P-wave vertical velocity v_{p0} and the S-wave vertical velocity v_{s0}) at the top and bottom of the layer,

$$\left| \frac{\Delta v_{p0}}{\bar{v}_{p0}} \right| \ll 1, \left| \frac{\Delta v_{s0}}{\bar{v}_{s0}} \right| \ll 1, \left| \frac{\Delta \rho}{\bar{\rho}} \right| \ll 1, \quad (24)$$

where $\Delta \alpha = \alpha^{(M)} - \alpha^{(A)}$, and $\bar{\alpha} = (\alpha^{(M)} + \alpha^{(A)})/2$ denote the difference and the average of the medium parameters α in the layer (corresponding to the superscript M) and background (corresponding to the superscript A).

Second, we assume weak anisotropy for both the layer and background:

$$|\epsilon^{(\mu)}| \ll 1, |\delta^{(\mu)}| \ll 1, \quad (25)$$

where the superscript μ is taken as M and A for the layer and background, respectively.

Finally, the VTI layer is assumed to be so thin that it satisfies the following inequality:

$$h q_p^{(M)} \omega < h q_s^{(M)} \omega \ll 1, \quad (26)$$

where $q_p^{(M)}$ and $q_s^{(M)}$ denote the vertical slowness components of P- and SV-waves, respectively in the layer, and are functions of the horizontal slowness component.

We start with equation 13 for reflection and transmission coefficients, where the propagator matrix B_{ij} is approximated by equation 2. The exponential functions in equations 16 and 17 are expanded with respect to $h q_p \omega$ and $h q_s \omega$, and then q_p and q_s are expanded with respect to horizontal slowness component. The horizontal slowness component is expressed in terms of the incidence angles θ_p and θ_s for the P- and SV-waves, respectively. The density and velocity parameters of the background medium and the layer are expressed in terms of their averages and differences. These operations allow us to expand the exact reflection coefficients with respect to the contrasts in the density, the velocities of vertically propagating P- and S-waves, the Thomsen anisotropy parameters, and the layer thicknesses normalized by the

velocities of the vertically propagating P- and S-waves. We also consider the expansion of the reflection coefficients with respect to the sine of the incident angles to obtain simple expressions for the approximate reflection coefficients. As a result, the approximate reflection coefficients are as follows.

P-P wave reflection coefficient:

$$R_{PP} \approx |r_{PP}| \exp(i\phi_{PP}) , \quad (27)$$

with

$$r_{PP} = \omega h (a_{PP} + b_{PP} \sin^2 \theta_p) , \quad (28)$$

$$\phi_{PP} = \frac{\pi}{2} \text{sign}(r_{PP}) + \tan^{-1} \left(\frac{\omega h}{\bar{v}_{p0}} \cos(\theta_p) \right) , \quad (29)$$

where θ_p denotes the angle of incidence of P-waves, and explicit expressions for a_{PP} and b_{PP} are given in equations B-1 and B-2 of Appendix B.

P-SV reflection coefficient:

$$R_{PS} \approx |r_{PS}| \exp(i\phi_{PS}) , \quad (30)$$

with

$$r_{PS} = \omega h \sin \theta_p (a_{PS} + b_{PS} \sin^2 \theta_p) , \quad (31)$$

$$\phi_{PS} = \frac{\pi}{2} \text{sign}(r_{PS}) + \tan^{-1} \left(\omega h \frac{c_{PS} + d_{PS} \sin^2 \theta_p}{a_{PS} + b_{PS} \sin^2 \theta_p} \right) , \quad (32)$$

where explicit expressions for a_{PS} , b_{PS} , c_{PS} and d_{PS} are given in equations B-3-B-6 of Appendix B.

SV-SV reflection coefficient:

$$R_{SS} \approx |r_{SS}| \exp(i\phi_{SS}) , \quad (33)$$

with

$$r_{ss} = \omega h (a_{ss} + b_{ss} \sin^2 \theta_s), \quad (34)$$

$$\phi_{ss} = \frac{\pi}{2} \text{sign}(r_{ss}) + \tan^{-1} \left(\frac{\omega h}{\bar{v}_{s0}} \cos(\theta_s) \right), \quad (35)$$

where θ_s denotes the angle of incidence of SV-waves, and explicit expressions for a_{ss} and b_{ss} are given in equations B-7 and B-8 of Appendix B.

SV-P reflection coefficient:

$$R_{sp} \approx |r_{sp}| \exp(i\phi_{sp}), \quad (36)$$

with

$$r_{sp} = \omega h \sin \theta_s (a_{sp} + b_{sp} \sin^2 \theta_s), \quad (37)$$

$$\phi_{sp} = \frac{\pi}{2} \text{sign}(r_{sp}) + \tan^{-1} \left(\omega h \frac{c_{sp} + d_{sp} \sin^2 \theta_s}{a_{sp} + b_{sp} \sin^2 \theta_s} \right). \quad (38)$$

where $a_{sp} = a_{ps}$, and explicit expressions for a_{ps} , b_{ps} , c_{ps} and d_{ps} are given in equations B-9-B-12 of Appendix B.

In equations 28 and 34, the coefficients a_{pp} and a_{ss} determine the magnitudes of the P-P and SV-SV reflection coefficients at normal incidence, and the coefficients b_{pp} and b_{ss} govern the curvatures of the reflection-coefficient magnitudes with respect to incidence angles. In equations 31 and 37, the coefficients a_{ps} and a_{sp} describe the gradients of the magnitudes of the P-SV and SV-P wave reflection coefficients with respect to the corresponding incidence angles, and the coefficients b_{ps} and b_{sp} describe the higher-order terms with respect to θ_p and θ_s . For small incidence angles, the converted-wave reflection coefficients are mostly controlled by the-coefficients a_{ps} and a_{sp} .

Referring to the equations in Appendix B, the approximate reflection coefficients indicate that (1) the reflection coefficients vanish when the layer thickness tends to zero, because the

medium properties above and below the layer are identical; (2) the magnitude of the reflection coefficients increases with frequency, albeit just for the limited frequency range in which the layer remains thin compared to the predominant wavelength; (3) the curvatures of the magnitudes of the P-P and SV-SV wave reflection coefficients with respect to the incidence angles are controlled by the changes in the anisotropy parameters δ and σ across the layer boundaries (σ is the combination of Thomsen parameters, defined after equation B-6); (4) the gradient and torsion of the magnitude of the P-SV wave reflection coefficient with respect to the incidence angle depend on the changes in δ and σ (respectively) across the layer boundaries; (5) the gradient of the magnitude of the SV-P wave reflection coefficient with respect to the incidence angle is identical to that of the P-SV wave reflection coefficient; (6) the torsion of the magnitude of the SV-P wave reflection coefficient with respect to the incidence angle involves the changes in both ε and δ across the layer boundaries, and cannot be described in terms of the single parameter σ .

Numerical examples

We use two single-layer models (Figure 1) to investigate the reflection coefficients of incident P- and SV-waves. The first model includes a high-velocity thin VTI layer embedded in a homogeneous isotropic background. The second model includes a low-velocity thin VTI layer embedded in the same isotropic background. The second model is obtained by reducing the layer velocities $v_{p0}^{(M)}$ and $v_{s0}^{(M)}$ from the first model, whereas all other parameters remain the same.

In the first example, we investigate the influence of wavelength on the P-P and S-S wave normal-incidence reflection coefficients (equations 18 and 19). Figures 2 and 3 show that those coefficients are periodic functions of wavelength. Comparison between Figures 2 and 3

shows that the magnitudes of the P-P and S-S reflection coefficients for the high- and low-velocity layers are similar, whereas the phases are different. When the layer thickness is much smaller than the wavelengths of the vertically propagating P- and S-waves inside the layer (i.e. $h / \lambda_{p0} \leq 0.2$ and $h / \lambda_{s0} \leq 0.2$), the magnitudes of the reflection coefficients have a sinusoidal shape, and the phases increase linearly with the normalized layer thickness.

Next, we investigate the influence of the anisotropy parameters on the reflection coefficients. The coefficients b_{pp} and b_{ss} determine the curvatures of the magnitudes of the P-P and SV-SV wave reflection coefficients with respect to the incidence angles. Figures 4 and 5 show that b_{pp} and b_{ss} vary linearly with the changes in δ and σ (respectively) across the layer boundaries. Comparison of Figures 6 and 7 indicates that the coefficients a_{ps} and b_{ps} , which determine the gradient and torsion of the magnitude of the P-SV wave reflection coefficients, also have a linear dependence on the changes in δ and σ (respectively) across the layer boundaries. The coefficients a_{sp} and b_{sp} control the magnitude of the P-SV wave reflection coefficients. The coefficient a_{sp} is identical to a_{ps} (equation B-9), whereas the coefficient b_{sp} (equation B-10) cannot be expressed in terms of the change in the single parameter σ , as discussed above. Figure 8 shows that the coefficient b_{sp} has an opposite dependence on the changes in the parameters ε and δ across the layer boundaries. This implies that simultaneous increases or decreases in $\Delta\varepsilon$ and $\Delta\delta$ partially cancel each other out in the coefficient b_{sp} .

In the third example, we test the accuracy of the approximate reflection coefficients (equations 27, 30, 33 and 36) for the low- and high-velocity layer models. The frequency of the incident waves is set to $f = 20\text{Hz}$. Figures 9-12 show the angular variation of the reflection coefficients for subcritical incidence. All approximate coefficients generally reproduce the correct trend of the exact solutions. The phases of all the reflection coefficients

vary with the incidence angle. The accuracy of the approximate P-P wave reflection coefficient is generally acceptable, especially for the low-velocity model (Figure 11(a)). The angular variation of the magnitudes of the P-P and SV-SV waves reflection coefficients for the low-velocity model (Figures 11(a) and 12(a)) is more significant than those for the high-velocity model (Figures 9(a) and 10(a)). The magnitudes of the P-SV and SV-P waves reflection coefficients for the high-velocity model (Figures 9(c) and 10(c)) are generally much smaller than that for the low-velocity model (Figures 11(c) and 12(c)). Except for the approximate P-P reflection coefficient, all other approximations produce significant errors either in amplitude or phase, so they should not be applied to AVO inversion. Higher-order expansions of the reflection coefficients with respect to the changes in the medium parameters across the layer boundaries may improve the accuracy of the solutions but would significantly increase their complexity.

Conclusions

The exact reflection and transmission coefficients for a thin VTI layer embedded in a VTI medium are derived using the propagator matrix method. The exact normal-incidence reflection and transmission coefficients, expressed in terms of the impedances of the vertically propagating P- and SV-wave, are periodic functions of wavelength and frequency. The magnitudes of the P-P and S-S wave normal-incidence reflection coefficients have a similar dependence on layer thickness. The phase curve of the P-P wave normal-incidence reflection coefficient for a low-velocity layer is similar to that of the S-S wave coefficient from a high-velocity layer, and vice versa.

In the case of subcritical incidence, the approximate reflection coefficients are derived under the following assumptions: (1) the layer thickness is much smaller than the wavelength of P-

and SV-waves inside the layer; (2) the contrasts in density and in the velocities of the vertically propagating P- and SV-waves are small; (3) the layer and the background are weakly anisotropic.

The influence of transverse isotropy on the reflection coefficients from the layer is described in terms of the changes in the anisotropy parameters across the layer boundaries. The change in the Thomsen parameter δ across the layer boundaries determines the anisotropy contribution to the P-P wave reflection coefficient, while the change in the anisotropy parameter σ contributes to the SV-SV wave reflection coefficient. The change in δ across the layer boundaries has the same influence on the gradient term of the magnitudes of the P-SV and SV-P wave reflection coefficients. The change in σ across the layer boundaries contributes to the torsion term of the magnitude of the P-SV wave reflection coefficients. The anisotropy contribution to the torsion terms of the SV-P wave reflection coefficients is determined by the changes in ε and δ , and cannot be expressed in terms of a single anisotropy coefficient.

Except for the approximate P-P wave reflection coefficient, the other obtained approximations for the reflection coefficients are not accurate enough for quantitative AVO analysis or AVO inversion. However, they provide analytic insight into the behavior of the reflection coefficients and may qualitatively guide numerical inversion based on the exact equations.

Acknowledgements

We thank rock and seismic (ROSE) project for support. The first author thanks V. Li, J. Cheng and an anonymous reviewer for their critical reviews, and especially thanks guest associate editor I. Tsvankin for his constructive review, many valuable suggestions and improving the English of the paper.

Appendix A Propagator matrix for a horizontal VTI layer

In this appendix, we adopt the method presented in Brekhovskikh (1980) to derive the propagator matrix for a horizontal VTI layer (Figure 1). The propagator matrix depends only on the layer parameters. For simplicity, we omit the superscript “ M ”, which is used to distinguish the layer from the upper and lower half-spaces, in the horizontal and vertical slowness components l and m and the vertical slowness component q . The in-plane wavefield inside the layer can always be represented by a superposition of up- and down-going P- and SV-waves. We define the following particle displacement functions of these waves,

$$\mathbf{u}_{p\downarrow} = A_{p\downarrow}(l_p, 0, m_p)^T \exp(-i\omega(t - px + q_p z)) , \quad (\text{A-1})$$

$$\mathbf{u}_{s\downarrow} = A_{s\downarrow}(l_s, 0, -m_s)^T \exp(-i\omega(t - px + q_s z)) , \quad (\text{A-2})$$

$$\mathbf{u}_{p\uparrow} = A_{p\uparrow}(l_p, 0, -m_p)^T \exp(-i\omega(t - px - q_p z)) , \quad (\text{A-3})$$

$$\mathbf{u}_{s\uparrow} = A_{s\uparrow}(l_s, 0, -m_s)^T \exp(-i\omega(t - px - q_s z)) , \quad (\text{A-4})$$

where subscripts “ $\uparrow$ ” and “ $\downarrow$ ” denote the up- and down-going waves, respectively; subscripts “ P ” and “ S ” denote P- and S-waves, respectively. The horizontal components of the unit polarization vectors of these waves are chosen to be nonnegative, which agrees with the convention used in Aki and Richards (2002) to derive the reflection and transmission coefficients for an interface separating two isotropic half-spaces.

The total displacement inside the layer is given by

$$\mathbf{u} = \mathbf{u}_{p\downarrow} + \mathbf{u}_{s\downarrow} + \mathbf{u}_{p\uparrow} + \mathbf{u}_{s\uparrow} . \quad (\text{A-5})$$

The components of the stress vector are expressed in terms of the displacement components (Graebner, 1992),

$$\tau_{zx} = c_{55} \left(\frac{\partial u_x}{\partial z} + \frac{\partial u_z}{\partial x} \right), \quad (\text{A-6})$$

$$\tau_{zz} = c_{13} \frac{\partial u_x}{\partial x} + c_{33} \frac{\partial u_z}{\partial z}, \quad (\text{A-7})$$

where τ_{zx} and τ_{zz} denote the horizontal and vertical components of the traction vector acting across a horizontal surface, and u_x and u_z denote the horizontal and vertical components of the particle displacement.

The displacements and tractions at the top and bottom of the layer are obtained by setting $z = 0$ and $z = h$ in equations A-5-A-7. As a result, we obtain eight linear equations involving the particle velocities and tractions at the top and bottom of the layer and the amplitudes of the up- and down-going waves, where the particle velocity is the first-order derivative of the particle displacement with respect to time. Canceling the amplitudes of the up- and down-going waves from these equations, we link the particle velocity and the traction at the bottom interface to the particle velocity and the traction at the top interface,

$$\begin{pmatrix} v_x \\ v_z \\ \tau_{zz} \\ \tau_{zx} \end{pmatrix} \bigg|_{z=0} = \begin{pmatrix} B_{11} & B_{12} & B_{13} & B_{14} \\ B_{21} & B_{22} & B_{23} & B_{24} \\ B_{31} & B_{32} & B_{33} & B_{34} \\ B_{41} & B_{42} & B_{43} & B_{44} \end{pmatrix} \begin{pmatrix} v_x \\ v_z \\ \tau_{zz} \\ \tau_{zx} \end{pmatrix} \bigg|_{z=h}, \quad (\text{A-8})$$

where v_x and v_z denote the horizontal and vertical components of the particle velocity, and B_{ij} is the transfer matrix. The elements B_{ij} are given by:

$$B_{14} = i(l_p m_s \sin(hq_p \omega) + l_s m_p \sin(hq_s \omega)) / (\xi c_{55}), \quad (\text{A-9})$$

$$B_{23} = i(l_S m_P \sin(hq_P \omega) + l_P m_S \sin(hq_S \omega)) / (\zeta c_{33}) , \quad (\text{A-10})$$

$$B_{32} = -i((c_{13} l_P p + c_{33} m_P q_P)(m_S p - l_S q_S) \sin(hq_P \omega) + (m_P p + l_P q_P)(c_{13} l_S p - c_{33} m_S q_S) \sin(hq_S \omega)) / \xi , \quad (\text{A-11})$$

$$B_{41} = -ic_{55}((m_P p + l_P q_P)(c_{13} l_S p - c_{33} m_S q_S) \sin(hq_P \omega) + (c_{13} l_P p + c_{33} m_P q_P)(m_S p - l_S q_S) \sin(hq_S \omega)) / (\zeta c_{33}) , \quad (\text{A-12})$$

$$B_{31} = B_{42} = c_{55}(m_P p + l_P q_P)(m_S p - l_S q_S)(\cos(hq_P \omega) - \cos(hq_S \omega)) / \xi , \quad (\text{A-13})$$

$$B_{21} = B_{43} = -ic_{55}(l_S(m_P p + l_P q_P) \sin(hq_P \omega) + l_P(m_S p - l_S q_S) \sin(hq_S \omega)) / (\zeta c_{33}) , \quad (\text{A-14})$$

$$B_{11} = B_{44} = (m_S(m_P p + l_P q_P) \cos(hq_P \omega) + m_P(-m_S p + l_S q_S) \cos(hq_S \omega)) / \xi , \quad (\text{A-15})$$

$$B_{13} = B_{24} = l_P l_S (-\cos(hq_P \omega) + \cos(hq_S \omega)) / (\zeta c_{33}) , \quad (\text{A-16})$$

$$B_{22} = B_{33} = (m_P(-m_S p + l_S q_S) \cos(hq_P \omega) + m_S(m_P p + l_P q_P) \cos(hq_S \omega)) / \xi , \quad (\text{A-17})$$

$$B_{12} = B_{34} = i(l_P(m_S p - l_S q_S) \sin(hq_P \omega) + l_S(m_P p + l_P q_P) \sin(hq_S \omega)) / \xi , \quad (\text{A-18})$$

with

$$\xi = l_P m_S q_P + l_S m_P q_S , \quad \zeta = l_S m_P q_P + l_P m_S q_S . \quad (\text{A-19})$$

Assuming the layer to be thin and weakly anisotropic, we can expand B_{ij} with respect to $hq_P \omega$ and $hq_S \omega$ up to second-order. Furthermore, q_P and q_S are approximated by their second-order series expansions with respect to the horizontal slowness p . Weak anisotropy approximation is also considered to derive simple approximation for B_{ij} . Finally, the approximation for B_{ij} is given by

$$\begin{pmatrix} B_{11} & B_{12} & B_{13} & B_{14} \\ B_{21} & B_{22} & B_{23} & B_{24} \\ B_{31} & B_{32} & B_{33} & B_{34} \\ B_{41} & B_{42} & B_{43} & B_{44} \end{pmatrix} \approx \begin{pmatrix} 1 & 0 & 0 & 0 \\ 0 & 1 & 0 & 0 \\ 0 & 0 & 1 & 0 \\ 0 & 0 & 0 & 1 \end{pmatrix} + ih\omega \begin{pmatrix} 0 & B_{12}^{(1)} & 0 & B_{14}^{(1)} \\ B_{21}^{(1)} & 0 & B_{23}^{(1)} & 0 \\ 0 & B_{32}^{(1)} & 0 & B_{34}^{(1)} \\ B_{41}^{(1)} & 0 & B_{43}^{(1)} & 0 \end{pmatrix} - h^2 \omega^2 \begin{pmatrix} B_{11}^{(2)} & 0 & B_{13}^{(2)} & 0 \\ 0 & B_{22}^{(2)} & 0 & B_{24}^{(2)} \\ B_{31}^{(2)} & 0 & B_{33}^{(2)} & 0 \\ 0 & B_{42}^{(2)} & 0 & B_{44}^{(2)} \end{pmatrix} , \quad (\text{A-20})$$

where

$$B_{21}^{(1)} = B_{43}^{(1)} = p((1 - 2r^2) + \delta) \quad (\text{A-21})$$

$$B_{12}^{(1)} = B_{34}^{(1)} = p, \quad (\text{A-22})$$

$$B_{14}^{(1)} = \frac{1}{\rho v_{s0}^2}, \quad (\text{A-23})$$

$$B_{23}^{(1)} = \frac{1}{\rho v_{p0}^2}, \quad (\text{A-24})$$

$$B_{32}^{(1)} = \rho, \quad (\text{A-25})$$

$$B_{41}^{(1)} = \rho(1 - 4p^2 v_{s0}^2 (1 - r^2)) + 2\delta \rho v_{p0}^2 (1 - 2r^2) p^2 - 2\varepsilon \rho v_{p0}^2 p^2, \quad (\text{A-26})$$

$$B_{11}^{(2)} = B_{44}^{(2)} = \frac{1}{2} \left(\frac{1}{v_{s0}^2} - p^2 (3 - 2r^2) \right) + \frac{\delta(2 - 3r^2)p^2}{2r^2} - \frac{\varepsilon p^2}{r^2}, \quad (\text{A-27})$$

$$B_{13}^{(2)} = B_{24}^{(2)} = \frac{(1 - r^2)p}{2\rho v_{s0}^2} + \frac{\delta p}{2\rho v_{s0}^2}, \quad (\text{A-28})$$

$$B_{22}^{(2)} = B_{33}^{(2)} = \frac{1}{2} (1 + (1 - 2r^2)p^2) + \frac{\delta p^2}{2}, \quad (\text{A-29})$$

$$B_{31}^{(2)} = B_{42}^{(2)} = (1 - r^2)(1 - 2v_{s0}^2 p^2) \rho p + \frac{1}{2} \delta \rho (1 + 2(1 - 2r^2)v_{p0}^2 p^2) p - \varepsilon \rho v_{p0}^2 p^3, \quad (\text{A-30})$$

with

$$r = \frac{v_{s0}}{v_{p0}}. \quad (\text{A-31})$$

Here, ε and δ are Thomsen (1986) parameters.

Appendix B The functions in the approximate reflection coefficients

In this Appendix, we give explicit expressions for the functions in the approximate reflection coefficients.

The functions a_{pp} and b_{pp} in equation 28 are given by

$$a_{pp} = -\frac{\Delta Z_p}{\bar{v}_{p0} \bar{Z}_p}, \quad (\text{B-1})$$

$$b_{pp} = \frac{1}{\bar{v}_{p0}} \left(4\bar{r}^2 \frac{\Delta G}{\bar{G}} - \frac{\Delta v_{p0}}{\bar{v}_{p0}} + \frac{\Delta Z_p}{2\bar{Z}_p} - \Delta\delta \right). \quad (\text{B-2})$$

where $\bar{r} = \bar{v}_{s0}/\bar{v}_{p0}$ denotes the ratio between the velocities of the vertically propagating P- and S-waves; $\bar{Z}_{p0} = \bar{\rho}\bar{v}_{p0}$ denotes the P-wave impedance; and $\bar{G} = \bar{\rho}\bar{v}_{s0}^2$ denotes the shear modulus.

The functions a_{ps} , b_{ps} , c_{ps} and d_{ps} in equations 31 and 32 are given by

$$a_{ps} = \frac{1+3\bar{r}+2\bar{r}^2}{2\bar{v}_{s0}} \frac{\Delta\rho}{\bar{\rho}} + \frac{2(1+\bar{r})}{\bar{v}_{p0}} \frac{\Delta v_{s0}}{\bar{v}_{s0}} - \frac{1}{2\bar{v}_{s0}} \Delta\delta, \quad (\text{B-3})$$

$$\begin{aligned} b_{ps} &= -\frac{3+8\bar{r}+5\bar{r}^2}{4\bar{v}_{p0}} \frac{\Delta\rho}{\bar{\rho}} - \frac{1+4\bar{r}+3\bar{r}^2}{\bar{v}_{p0}} \frac{\Delta v_{s0}}{\bar{v}_{s0}} - \frac{1}{\bar{v}_{s0}} (\Delta\varepsilon - \Delta\delta) \\ &\approx -\frac{3+8\bar{r}+5\bar{r}^2}{4\bar{v}_{p0}} \frac{\Delta\rho}{\bar{\rho}} - \frac{1+4\bar{r}+3\bar{r}^2}{\bar{v}_{p0}} \frac{\Delta v_{s0}}{\bar{v}_{s0}} - \frac{\bar{r}^2}{\bar{v}_{s0}} \Delta\sigma, \end{aligned} \quad (\text{B-4})$$

$$c_{ps} = \frac{(1+\bar{r})^2(1+2\bar{r})}{4\bar{v}_{s0}^2} \frac{\Delta\rho}{\bar{\rho}} + \frac{(1+\bar{r})^2}{\bar{v}_{p0}\bar{v}_{s0}} \frac{\Delta v_{s0}}{\bar{v}_{s0}} - \frac{1+\bar{r}}{4\bar{v}_{s0}^2} \Delta\delta, \quad (\text{B-5})$$

$$\begin{aligned} d_{ps} &= -\frac{(1+\bar{r})^2(4+7\bar{r})}{8\bar{v}_{p0}\bar{v}_{s0}} \frac{\Delta\rho}{\bar{\rho}} - \frac{(1+\bar{r})^2(1+4\bar{r})}{2\bar{v}_{p0}\bar{v}_{s0}} \frac{\Delta v_{s0}}{\bar{v}_{s0}} \\ &\quad - \frac{1+\bar{r}}{2\bar{v}_{s0}^2} \Delta\varepsilon + \frac{4+5\bar{r}+\bar{r}^2}{8\bar{v}_{s0}^2} \Delta\delta, \end{aligned} \quad (\text{B-6})$$

where $\sigma \equiv (\nu_{p0}/\nu_{s0})^2(\varepsilon - \delta)$ is the combination of Thomsen parameters primarily responsible for SV-wave propagation (Tsvankin, 2012, equation 1.67).

The functions a_{ss} and b_{ss} in equation 34 are given by

$$a_{ss} = \frac{1}{\bar{\nu}_{s0}} \left(\frac{\Delta G}{\bar{G}} - \frac{\Delta \nu_{s0}}{\bar{\nu}_{s0}} \right), \quad (\text{B-7})$$

$$\begin{aligned} b_{ss} &= -\frac{1}{\bar{\nu}_{s0}} \left(\frac{9}{2} \frac{\Delta G}{\bar{G}} - \frac{3}{2} \frac{\Delta \nu_{s0}}{\bar{\nu}_{s0}} + \frac{1}{\bar{r}^2} (\Delta \varepsilon - \Delta \delta) \right) \\ &\approx -\frac{1}{\bar{\nu}_{s0}} \left(\frac{9}{2} \frac{\Delta G}{\bar{G}} - \frac{3}{2} \frac{\Delta \nu_{s0}}{\bar{\nu}_{s0}} + \Delta \sigma \right), \end{aligned} \quad (\text{B-8})$$

where σ is defined after equation B-6.

The functions a_{sp} , b_{sp} , c_{sp} and d_{sp} in equations 37 and 38 are given by

$$a_{sp} = a_{ps}, \quad (\text{B-9})$$

$$\begin{aligned} b_{sp} &= \frac{1}{\bar{\nu}_{p0}} \left(\frac{1 - 7\bar{r}^2 - 8\bar{r}^3 - 2\bar{r}^4}{4\bar{r}^3} \frac{\Delta \rho}{\bar{\rho}} - \frac{3 + 4\bar{r} + \bar{r}^2}{\bar{r}} \frac{\Delta \nu_{s0}}{\bar{\nu}_{s0}} \right) \\ &\quad - \frac{1}{\bar{\nu}_{s0}} \left(\frac{1}{\bar{r}^2} \Delta \varepsilon - \frac{3 + \bar{r}^2}{4\bar{r}^2} \Delta \delta \right), \end{aligned} \quad (\text{B-10})$$

$$c_{sp} = c_{ps}, \quad (\text{B-11})$$

$$\begin{aligned} d_{sp} &= \frac{(1 + \bar{r})^2 (1 - 2\bar{r} - 8\bar{r}^2 - 2\bar{r}^3)}{8\bar{r}^2 \bar{\nu}_{s0}^2} \frac{\Delta \rho}{\bar{\rho}} - \frac{(1 + \bar{r})^2 (4 + \bar{r})}{2\bar{\nu}_{s0}^2} \frac{\Delta \nu_{s0}}{\bar{\nu}_{s0}} \\ &\quad - \frac{1 + \bar{r}}{2\bar{r}^2 \bar{\nu}_{s0}^2} \Delta \varepsilon + \frac{3 + 4\bar{r} + 2\bar{r}^2 + \bar{r}^3}{8\bar{r}^2 \bar{\nu}_{s0}^2} \Delta \delta, \end{aligned} \quad (\text{B-12})$$

where a_{ps} and c_{ps} are given in equations B-3 and B-5.

REFERENCES

- Aki, K., and P.G. Richards, 2002, Quantitative seismology (2nd ed.), University Science Books.
- Brekhovskikh, L.M., 1980, Waves in layered media (2nd ed.), translated by R. T. Beyer: Academic Press.
- Brekhovskikh, L.M. and O. A. Godin, 1989, Acoustics of layered Media I: plane and quasi-plane Waves: Springer.
- Chapman, C., 2004, Fundamentals of seismic wave propagation: Cambridge University Press.
- Fryer, G. J., and L. N. Frazer, 1984, Seismic waves in stratified anisotropic media: Geophysical Journal of the Royal Astronomical Society, **78**, 691-710.
- Fryer, G. J., and L. N. Frazer, 1987, Seismic waves in stratified anisotropic media, II, Elastodynamic eigensolutions for some anisotropic systems: Geophysical Journal of the Royal Astronomical Society, **91**, 73-101.
- Graebner, M., 1992, Plane-wave reflection and transmission coefficients for a transversely isotropic solid: Geophysics, **57**, 1512-1519.
- Kennett, B. L. N., 1983, Seismic wave propagation in stratified media: Cambridge University Press.
- Nayfeh, A.H., 1995, Wave Propagation in layered anisotropic Media: North-Holland.
- Ursin, B. and G. U. Haugen, 1996, Weak-contrast approximation of the elastic scattering matrix in anisotropic media: Pure and Applied Geophysics, **148**, 685-714.
- Vavryčuk, V., 1999, Weak-contrast reflection/transmission coefficients in weakly anisotropic elastic media: P-wave incidence: Geophysical Journal International, **138**, 553-562.

Vavryčuk, V. and Pšenčík, I., 1998, PP wave reflection coefficients in weakly anisotropic elastic media: *Geophysics*, **63**, 2129-2141.

Rüger, A., 1996, Reflection coefficients and azimuthal AVO-analysis in anisotropic media: Ph.D thesis, Colorado School of Mines.

Rüger, A., 1997, P-wave reflection coefficients for transversely isotropic models with vertical and horizontal axis of symmetry: *Geophysics*, **62**, 713-722.

Rüger, A., 1998, Variation of P-wave reflectivity with offset and azimuth in anisotropic media: *Geophysics*, **63**, 935-947.

Schoenberg, M., 1983, Reflection of elastic waves from periodically stratified media with interfacial slip: *Geophysical Prospecting*, **31**, 265-292.

Thomsen, L., 1986, Weak elastic anisotropy: *Geophysics*, **51**, 1954-1966.

Thomsen, L., 1993, Weak anisotropic reflections. In: Offset dependent reflectivity (Castagna and Backus, Eds.): SEG.

Tsvankin, I., 2012, Seismic signatures and analysis of reflection data in anisotropic media (3rd ed.): SEG.

Figure captions

Figure 1. Schematic plots for plane-wave reflection and transmission from a single VTI layer: (a) P-wave incidence and (b) SV-wave incidence. The waves propagate in the $[x, z]$ plane of a Cartesian coordinate system. The symbol “ A ” denotes the homogeneous VTI background, and “ M ” denotes the layer. On plot (a), I_P , R_{PP} , R_{PS} , T_{PP} , and T_{PS} denote the incident P-wave, the P-P reflected wave, the P-SV reflected wave, the P-P transmitted wave, and the P-SV transmitted wave, respectively. On plot (b), I_S , R_{SP} , R_{SS} , T_{SP} , and T_{SS} denote the incident SV-wave, the SV-P reflected wave, the SV-SV reflected wave, the SV-P transmitted wave, and the SV-SV transmitted wave, respectively.

Figure 2. P-P and S-S wave normal-incidence reflection coefficients for the high-velocity VTI layer as a function of the layer thickness normalized by the wavelength. Plots (a) and (b) show the magnitude and phase of P-P wave reflection coefficient. Plots (c) and (d) show the magnitude and phase of S-S wave reflection coefficient. λ_{p0} and λ_{s0} denote the wavelengths of vertically propagating P- and S-waves inside the layer, respectively, and h is the layer thickness. The parameters of the isotropic background include: $v_{p0}^{(A)} = 3.0$ km/s , $v_{s0}^{(A)} = 1.5$ km/s , and $\rho^{(A)} = 2.6$ g/cm³ , and the parameters of the VTI layer include: $v_{p0}^{(M)} = 3.2$ km/s , $v_{s0}^{(M)} = 1.6$ km/s , $\rho^{(M)} = 2.8$ g/cm³ , $\epsilon^{(M)} = 0.1$, $\delta^{(M)} = 0.2$, and $h = 15$ m .

Figure 3. Similar to Figure 2, but for the low-velocity layer model. The vertical velocities in the layer are changed to $v_{p0}^{(M)} = 2.8$ km/s and $v_{s0}^{(M)} = 1.4$ km/s , while the other model parameters are the same as for the model in Figure 2.

Figure 4. The dependence of the coefficient b_{pp} (equation B-2) on the change in the parameter δ across the layer boundaries. The black and gray lines correspond to the high- and low-velocity layer models, respectively. The medium parameters of both models are explained in the captions of Figures 2 and 3, respectively; only the parameter $\delta^{(M)}$ of the layer is changed to generate the dependence on $\Delta\delta$.

Figure 5. The dependence of the coefficient b_{ss} (equation B-8) on the change in the parameter σ across the layer boundaries. The black and gray lines correspond to high- and low-velocity layer models, respectively. The high- and low-velocity layer models are explained in the captions of Figures 2 and 3, respectively; only the parameter $\delta^{(M)}$ is changed to generate the dependence on σ .

Figure 6. The dependence of coefficients a_{ps} (equation B-3) and a_{sp} (equation B-9) on the changes in the parameter δ across the layer boundaries. The black and gray lines correspond to the high- and low-velocity layer models, respectively. The high- and low-velocity models are explained in the captions of Figures 2 and 3, respectively.

Figure 7. Similar to Figure 5, but for the coefficient b_{ps} (equation B-4).

Figure 8. Variation of the coefficient b_{sp} (equation B-10) with the changes in the parameters (a) ε and (b) δ across the layer boundaries. The black and gray lines correspond to the high-

and low-velocity layer models, respectively. The models are designed in a way similar to that explained in Figure 2, except that $\Delta\delta=0$ and $\varepsilon^{(M)}$ is changed to obtain $\Delta\varepsilon$ in plot (a), whereas $\Delta\varepsilon=0$ and $\delta^{(M)}$ is changed to obtain $\Delta\delta$ in plot (b).

Figure 9. P-P and P-SV wave reflection coefficients for the high-velocity layer. The medium parameters are given in Figure 2. Plots (a) and (b) show the magnitude and phase respectively of the P-P wave reflection coefficient. Plots (c) and (d) show the magnitude and phase respectively of the P-SV wave reflection coefficient. The red and blue lines mark the exact and approximate solutions, respectively.

Figure 10. SV-SV and SV-P wave reflection coefficients for the high-velocity layer. The medium parameters are given in Figure 2. Plots (a) and (b) show the magnitude and phase respectively of the SV-SV wave reflection coefficient. Plots (c) and (d) show the magnitude and phase respectively of the SV-P wave reflection coefficient. The red and blue lines mark the exact and approximate solutions, respectively.

Figure 11. Similar to Figure 9, but for the low-velocity layer. The medium parameters are given in the captions of Figures 2 and 3.

Figure 12. Similar to Figure 10, but for the low-velocity layer. The medium parameters are shown in the captions of Figures 2 and 3.

1a

58x40mm (600 x 600 DPI)

1b

58x40mm (600 x 600 DPI)

2a

65x42mm (300 x 300 DPI)

2b

65x41mm (300 x 300 DPI)

2c

65x42mm (300 x 300 DPI)

2d

63x39mm (300 x 300 DPI)

3a

65x42mm (300 x 300 DPI)

3b

63x39mm (300 x 300 DPI)

3c

65x42mm (300 x 300 DPI)

3d

65x41mm (300 x 300 DPI)

4

62x38mm (300 x 300 DPI)

5

66x43mm (300 x 300 DPI)

6

64x40mm (300 x 300 DPI)

7

62x38mm (300 x 300 DPI)

8a

66x44mm (300 x 300 DPI)

8b

64x40mm (300 x 300 DPI)

9a

67x45mm (300 x 300 DPI)

9b

68x46mm (300 x 300 DPI)

9c

66x43mm (300 x 300 DPI)

9d

68x46mm (300 x 300 DPI)

10a

64x41mm (300 x 300 DPI)

10b

68x46mm (300 x 300 DPI)

10c

66x43mm (300 x 300 DPI)

10d

68x46mm (300 x 300 DPI)

11a

67x45mm (300 x 300 DPI)

11b

68x46mm (300 x 300 DPI)

11c

67x45mm (300 x 300 DPI)

11d

68x46mm (300 x 300 DPI)

12a

67x45mm (300 x 300 DPI)

12b

68x45mm (300 x 300 DPI)

12c

67x45mm (300 x 300 DPI)

12d

68x46mm (300 x 300 DPI)