Asymptotic analysis of RZF in large-scale MU-MIMO systems over Rician channels

Abla Kammoun, *Member, IEEE*, Luca Sanguinetti, *Senior Member, IEEE*, Merouane Debbah, *Fellow, IEEE* and Mohamed-Slim Alouini *Fellow, IEEE*

Abstract—In this work, we focus on the downlink ergodic sum rate of a single-cell large-scale multiuser MIMO system in which the base station employs N antennas to communicate with K single-antenna user equipments (UEs). A regularized zero-forcing (RZF) scheme is used for precoding under the assumption that each UE uses a specific power and each link forms a spatially correlated MIMO Rician fading channel. The analysis is conducted assuming that N and K grow large with a non trivial ratio and perfect channel state information is available at the base station. New results from random matrix theory and large system analysis are used to compute an asymptotic expression of the signal-to-interference-plus-noise ratio as a function of the system parameters, the spatial correlation matrix and the Rician factor. Numerical results are used to validate the accuracy of the asymptotic approximations in the finite system regime and to evaluate the performance under different operating conditions. It turns out that the provided asymptotic expressions provide accurate approximations even for relatively small values of N and K .

I. INTRODUCTION

Large-scale multiple-input multiple-output (MIMO) systems are considered as one of the most promising technology for next generation wireless communication systems [1]–[4] because of their considerable spatial multiplexing gains. The use of large-scale MIMO systems is beneficial not only in terms of coverage and spectral efficiency but also in terms of energy-saving [5]–[7]. In this complex system model, a number of practical factors such as correlation effects and line-of-sight (LoS) components need to be included, which occur due to the space limitation of user equipments (UEs) and the densification of the antenna arrays resulting in a visible propagation path from the UEs, respectively. For typical systems of hundreds of antennas and tens of UEs, Monte Carlo simulations become challenging, thereby making performance analysis of large-scale MIMO systems an important subject of research.

A. Major contributions

In this work, we consider the downlink of a single-cell large-scale MIMO system in which the base station (BS), equipped

with N antennas, makes use of regularized zero-forcing (RZF) precoding to communicate with K single-antenna UEs. In particular, we are interested in evaluating the ergodic sum rate of the system when UEs transmit with different power levels and a power constraint is imposed at the BS. The analysis is conducted assuming that N and K grow large with a non trivial ratio under the assumption that perfect channel state information is available at the BS. Differently from most of the existing literature [8]–[12], we consider a spatially correlated MIMO Rician fading model, which is more general and accurate to capture the fading variations when there is a LoS component. Compared to the Rayleigh fading channel, a Rician model makes the asymptotic analysis of large-scale MIMO systems much more involved with the difficulty lying in handling the non-uniform power allocation across the UEs and the dependency between the precoding matrix and the non-centered channels. To overcome this issue, recent results from random matrix theory and large system analysis [12]–[14] are used to compute an asymptotic expression of the signal-to-interference-plus-noise ratio (SINR), which is eventually used to approximate the ergodic sum rate of the system. As shall be seen, the results are found to depend only on the system parameters, the spatial correlation matrix and the Rician factor. As a notable outcome of this work, the above analysis provides an analytical framework that can be used to evaluate the performance of the network under different settings without resorting to heavy Monte Carlo simulations and to eventually get insights on how the different parameters affect the performance. Further insights on the impact of the LoS components are obtained for simpler case studies. The conference version of this paper considers uniform power allocation, contains only a subset of the analysis and no technical proofs. Moreover, this work further extends the random matrix theory results provided in [13], that are instrumental to perform the large system analysis under Rician fading channels.

B. State-of-the-art

The main literature related to this work is represented by [8], [11], [15]–[17]. Tools from random matrix theory are used in [8] to compute the ergodic sum rate in a single-cell setting with Rayleigh fading and different precoding schemes while the multicell case is analyzed in [11]. In [15], the authors investigate a LoS-based conjugate beamforming transmission scheme and derive some expressions of the statistical SINR under the assumption that N grows large and K maintain fixed. In [16], the authors study the fluctuations of the mutual information of a cooperative small cell network operating over a Rician fading channel under the form of a central limit

A. Kammoun and M.-S. Alouini are with the Electrical Engineering Department, King Abdullah University of Science and Technology, Thuwal, Saudi Arabia. L. Sanguinetti is with the University of Pisa, Dipartimento di Ingegneria dell'Informazione, Italy (luca.sanguinetti@unipi.it) and also with the Large Systems and Networks Group (LANEAS), CentraleSupélec, Université Paris-Saclay, 3 rue Joliot-Curie, 91192 Gif-sur-Yvette, France. M. Debbah is the Large Systems and Networks Group (LANEAS), CentraleSupélec, Université Paris-Saclay, 3 rue Joliot-Curie, 91192 Gif-sur-Yvette, France (m.debbah@centralesupélec.fr) and also with the Mathematical and Algorithmic Sciences Lab, Huawei Technologies Co. Ltd., France (merouane.debbah@huawei.com).

A preliminary version of this paper was presented at the 41st IEEE International Conference on Acoustics, Speech and Signal Processing (ICASSP 2016), Shanghai, China, 20–25 March 2016.

theorem and provide explicit expression of the asymptotic variance. In [17], a deterministic equivalent of the ergodic sum rate and an algorithm for evaluating the capacity achieving input covariance matrices for the uplink of a large-scale MIMO are proposed for spatially correlated MIMO channel with LoS components. The analysis of the uplink rate with both zero-forcing and maximum ratio combining receivers is performed in [18]. In [19], the authors derive tractable expressions for the achievable UL rate for ZF and MRC in the large-antenna limit, along with approximating results that hold for any finite number of antennas (N grows large and K is fixed). Based on these analytical results, the transmit power scaling law to meet a desirable quality of service is computed. A numerical analysis is used in [20] to show how LoS components may potentially improve the system performance and mitigate the pilot contamination problem. In [21], a full-duplex multicell Massive MIMO systems is analyzed. A deterministic approximation of the UL achievable rate with MRC is derived based on random matrix theory. In [22], a detailed achievable rate analysis of regular and large-scale single-user MIMO systems is presented under transceiver hardware impairments and Rician fading conditions.

C. Outline and notation

The remainder of this work is organized as follows. Next section introduces the system and channel models. The main results are provided in Section III, where the random matrix theory tools used in [13] are first extended and then use to compute deterministic approximations of the SINR under RZF precoding. A few case studies are also considered to get further insights into the effect of system parameters. Numerical results are used in Section IV to validate the theoretical analysis for systems of finite size and to investigate the performance of the network under different operating conditions. Finally, the major conclusions are drawn in Section V. All the technical proofs are presented in the Appendices.

The following notation is used throughout this work. The superscript H stands for the conjugate transpose operation. The operator $\text{Tr}(\mathbf{X})$ denotes trace of matrix $\mathbf{X}$ whereas $\mathbf{X}_{[k]}$ indicates that the k th column is removed from matrix $\mathbf{X}$. The Frobenius and spectral norms of a matrix $\mathbf{X}$ are denoted by $\|\mathbf{X}\|_F$ and $\|\mathbf{X}\|_2$, respectively. The $N \times N$ identity matrix is denoted by $\mathbf{I}_N$ whereas $\mathbf{X} = \text{diag}\{x_1, \dots, x_N\}$ is used to denote a $N \times N$ diagonal matrix of entries $\{x_n\}$. A random variable x is a standard complex Gaussian variable if $x \sim \mathcal{CN}(0, 1)$. We use $a_n - b_n \rightarrow 0$ to denote $a_n - b_n \rightarrow_{n \rightarrow \infty} 0$ (almost surely (a.s.)) for two (random) sequences a_n, b_n .

II. SYSTEM AND CHANNEL MODELS

We consider the DL of a network in which K UEs are served by a single BS equipped with N antennas. Denoting by $\mathbf{g}_i \in \mathbb{C}^N$ the precoding vector associated to UE i , the received signal y_k at a generic UE k takes the form [8]

$$y_k = \sqrt{\xi} \mathbf{h}_k^H \sum_{i=1}^K \mathbf{g}_i \varsigma_i + n_k \quad (1)$$

where $\varsigma_i \sim \mathcal{CN}(0, p_i)$ is the data symbol intended to UE i with variance $p_i \geq 0$, $\mathbf{h}_k \in \mathbb{C}^N$ is the random channel vector from the BS to UE k , and $n_k \sim \mathcal{CN}(0, \sigma^2)$ accounts for thermal noise. As shown next, the parameter ξ normalizes the average transmit power. For analytic tractability, we assume that the BS has perfect channel state information. The precoding matrix $\mathbf{G} = [\mathbf{g}_1 \dots \mathbf{g}_K] \in \mathbb{C}^{N \times K}$ is designed according to the RZF scheme as follows [8]

$$\mathbf{G} = (\mathbf{H}\mathbf{H}^H + \lambda N \mathbf{I}_N)^{-1} \mathbf{H} \quad (2)$$

where $\mathbf{H} = [\mathbf{h}_1, \dots, \mathbf{h}_K] \in \mathbb{C}^{N \times K}$ is the aggregate channel matrix, $\lambda > 0$ is the so-called regularization parameter and ξ is chosen to satisfy the following power constraint

$$\frac{\xi}{K} \text{Tr}(\mathbf{P}\mathbf{G}^H \mathbf{G}) = P_T \quad (3)$$

where $\mathbf{P} = \text{diag}\{p_1, \dots, p_K\}$ and $P_T > 0$ denotes the total available transmit power. Plugging (2) into (3) yields

$$\xi = \frac{P_T}{\frac{1}{K} \text{Tr}(\mathbf{P}\mathbf{H}^H (\mathbf{H}\mathbf{H}^H + \lambda N \mathbf{I}_N)^{-2} \mathbf{H})}. \quad (4)$$

Under the assumption of Gaussian signaling, i.e., $\varsigma_k \sim \mathcal{CN}(0, p_k)$ and single-user detection with perfect channel state information at the receiver, the SINR γ_k of UE k takes the form

$$\gamma_k = \frac{p_k |\mathbf{h}_k^H \mathbf{g}_k|^2}{\sum_{i=1, i \neq k}^K p_i |\mathbf{h}_k^H \mathbf{g}_i|^2 + \frac{\sigma^2}{\xi}}. \quad (5)$$

The rate r_k of UE k is given by $r_k = \log_2(1 + \gamma_k)$ whereas the ergodic sum rate is defined as

$$r_E = \sum_{k=1}^K \mathbb{E} [\log_2(1 + \gamma_k)] \quad (6)$$

where the expectation is taken over the random channel vectors $\{\mathbf{h}_k : k = 1, \dots, K\}$. We assume that $\mathbf{h}_k = \sqrt{\beta_k} \mathbf{w}_k$ where β_k accounts for the large-scale channel fading gain of UE k and $\mathbf{w}_k \in \mathbb{C}^N$ is the small-scale fading channel component. The latter is modelled as

$$\mathbf{w}_k = \sqrt{\frac{1}{1 + \rho}} \boldsymbol{\Theta}^{1/2} \mathbf{z}_k + \sqrt{\frac{\rho}{1 + \rho}} \tilde{\mathbf{z}}_k \quad (7)$$

where $\mathbf{z}_k \in \mathbb{C}^N$ is assumed to be Gaussian with zero mean and unit covariance, i.e., $\mathbf{z}_k \sim \mathcal{CN}(\mathbf{0}_N, \mathbf{I}_N)$, and $\tilde{\mathbf{z}}_k \in \mathbb{C}^N$ is a deterministic vector. The scalar $\rho \geq 0$ is the Rician factor whereas the matrix $\boldsymbol{\Theta}^{1/2}$ is obtained from the Cholesky decomposition of $\boldsymbol{\Theta} \in \mathbb{C}^{N \times N}$, which accounts for the channel correlation matrix at the BS antennas. To make the problem analytically more tractable, we consider a system with a common UE channel correlation matrix [8], [23], [24]. Despite possible in principle, the extension to the case in which UEs have different channel correlation matrices is mathematically much more involved and it is left for future work. In practice, the considered scenario may arise in networks wherein the UEs are clustered on the basis of their covariance matrices such that UEs with different covariance matrices are put in different clusters [23], [25].

III. MAIN RESULTS

We aim to exploit the statistical distribution of the channel matrix $\mathbf{H} = [\mathbf{h}_1 \dots \mathbf{h}_K] \in \mathbb{C}^{N \times K}$ and the large dimensions of N and K to compute a deterministic approximation of γ_k , which will be eventually used to find an approximation of the ergodic sum rate. In doing so, we assume the following growth rate of system dimensions:

Assumption 1. *The dimensions N and K grow to infinity at the same pace, that is:*

$$1 \leq \liminf N/K \leq \limsup N/K < \infty. \quad (8)$$

A. Preliminaries

To begin with, we call

$$\tilde{\mathbf{D}} = \text{diag} \left\{ \frac{\beta_1}{1+\rho}, \dots, \frac{\beta_K}{1+\rho} \right\} \quad (9)$$

and compute the eigendecomposition of $\Theta^{1/2}$ to obtain $\Theta^{1/2} = \mathbf{U}^H \mathbf{D}^{1/2} \mathbf{U}$ with $\mathbf{U} \in \mathbb{C}^{N \times N}$ being unitary. Then, we rewrite $\mathbf{H}$ as follows $\mathbf{H} = \sqrt{N} \mathbf{U}^H \Sigma$ where Σ is defined as

$$\Sigma = \frac{1}{\sqrt{N}} \mathbf{D}^{1/2} \mathbf{X} \tilde{\mathbf{D}}^{1/2} + \mathbf{A} \quad (10)$$

with $\mathbf{X} = \mathbf{U} \mathbf{Z}$, $\mathbf{Z} = [\mathbf{z}_1, \dots, \mathbf{z}_K]$, $\mathbf{A} = \mathbf{U} \tilde{\mathbf{Z}}$ and

$$\tilde{\mathbf{Z}} = \sqrt{\frac{1}{N} \frac{\rho}{1+\rho}} \left[\sqrt{\beta_1} \tilde{\mathbf{z}}_1, \dots, \sqrt{\beta_K} \tilde{\mathbf{z}}_K \right]. \quad (11)$$

Plugging $\mathbf{H} = \sqrt{N} \mathbf{U}^H \Sigma$ into (2) and (4) yields

$$\mathbf{G} = \frac{1}{\sqrt{N}} \mathbf{U}^H \left(\Sigma \Sigma^H + \lambda \mathbf{I}_N \right)^{-1} \Sigma \quad (12)$$

and

$$\xi = \frac{NP_T}{\frac{1}{K} \text{Tr}(\mathbf{P} \Sigma^H (\Sigma \Sigma^H + \lambda \mathbf{I}_N)^{-2} \Sigma)}. \quad (13)$$

To derive a deterministic equivalent of the SINR under RZF precoding, we require the following assumptions on the correlation matrix Θ and on the matrix $\mathbf{A}$ collecting the LoS components of UE channels [8], [13], [14]. They are a common way to model that the array gathers more energy as N increases and also that this energy originates from many spatial dimensions.

Assumption 2. *As $N, K \rightarrow \infty$, $\limsup_N \|\Theta\|_2 < \infty$ and $\inf_N \frac{1}{N} \text{Tr}(\Theta) > 0$.*

Assumption 3. *As $N, K \rightarrow \infty$, $\limsup_N \|\mathbf{A}\|_2 < \infty$ and $\inf_N \frac{1}{N} \text{Tr}(\mathbf{A}) > 0$.*

Let us also introduce the fundamental equations that are needed to express a deterministic equivalent of γ_k . We start with the following set of equations:

$$\delta = \frac{1}{N} \text{Tr}(\mathbf{D} \mathbf{T}) \quad (14)$$

$$\tilde{\delta} = \frac{1}{N} \text{Tr}(\tilde{\mathbf{D}} \tilde{\mathbf{T}}) \quad (15)$$

TABLE I
LIST OF DETERMINISTIC QUANTITIES THAT ARE EXTENSIVELY USED IN THIS PAPER.

Variable	Deterministic expression
ϑ	$\frac{1}{N} \text{Tr}(\mathbf{D} \mathbf{T} \mathbf{D} \mathbf{T})$
$\tilde{\vartheta}$	$\frac{1}{N} \text{Tr}(\tilde{\mathbf{D}} \tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}})$
F	$\frac{1}{N} \text{Tr} \left(\tilde{\mathbf{D}} \tilde{\mathbf{T}} \mathbf{A}^H (\mathbf{I}_N + \tilde{\delta} \mathbf{D})^{-1} \mathbf{D} (\mathbf{I}_N + \tilde{\delta} \mathbf{D})^{-1} \mathbf{A} \tilde{\mathbf{T}} \right)$
Δ	$(1 - F)^2 - \lambda^2 \vartheta \tilde{\vartheta}$
α	$\frac{1}{N} \text{Tr}(\mathbf{D} \mathbf{T}^2)$
V	$\frac{1}{N} \text{Tr} \left(\tilde{\mathbf{D}} \tilde{\mathbf{T}} \mathbf{A}^H (\mathbf{I}_N + \tilde{\delta} \mathbf{D})^{-2} \mathbf{A} \tilde{\mathbf{T}} \right)$
$\tilde{\gamma}_\ell$	$\left[\tilde{\mathbf{T}} \mathbf{A}^H \mathbf{D} (\mathbf{I}_K + \tilde{\delta} \mathbf{D})^{-2} \mathbf{A} \tilde{\mathbf{T}} \right]_{\ell\ell}$

with

$$\mathbf{T} = \left(\lambda (\mathbf{I}_N + \tilde{\delta} \mathbf{D}) + \mathbf{A} (\mathbf{I} + \delta \tilde{\mathbf{D}})^{-1} \mathbf{A}^H \right)^{-1} \quad (16)$$

$$\tilde{\mathbf{T}} = \left(\lambda (\mathbf{I}_K + \delta \tilde{\mathbf{D}}) + \mathbf{A}^H (\mathbf{I}_N + \tilde{\delta} \mathbf{D})^{-1} \mathbf{A} \right)^{-1} \quad (17)$$

which admit unique positive solutions in the class of Stieltjes transforms of non-negative measures with support $\mathbb{R}_+$ [13], [14]. The matrices $\mathbf{T}$ and $\tilde{\mathbf{T}}$ are approximations of the resolvent $\mathbf{Q} = (\Sigma \Sigma^H - z \mathbf{I}_N)^{-1}$ and the co-resolvent $\tilde{\mathbf{Q}} = (\Sigma^H \Sigma - z \mathbf{I}_K)^{-1}$ such that

$$\frac{1}{N} \text{Tr}(\mathbf{B} \mathbf{Q}) - \frac{1}{N} \text{Tr}(\mathbf{B} \mathbf{T}) \rightarrow 0 \quad (18)$$

$$\frac{1}{N} \text{Tr}(\tilde{\mathbf{B}} \tilde{\mathbf{Q}}) - \frac{1}{N} \text{Tr}(\tilde{\mathbf{B}} \tilde{\mathbf{T}}) \rightarrow 0 \quad (19)$$

for any sequence of matrices $\mathbf{B} \in \mathbb{C}^{N \times N}$ and $\tilde{\mathbf{B}} \in \mathbb{C}^{K \times K}$ and

$$\mathbb{E} |\mathbf{u}^H \mathbf{Q} \mathbf{u} - \mathbf{u}^H \mathbf{T} \mathbf{u}|^p = \mathcal{O}(N^{-p/2}) \quad (20)$$

$$\mathbb{E} |\mathbf{u}^H \tilde{\mathbf{Q}} \mathbf{u} - \mathbf{u}^H \tilde{\mathbf{T}} \mathbf{u}|^p = \mathcal{O}(N^{-p/2}) \quad (21)$$

for any integer p and any sequence of vectors $\mathbf{u} \in \mathbb{C}^N$ with uniformly bounded norm. For later convenience, we also observe that

$$\mathbf{T} \mathbf{A} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} = (\mathbf{I}_N + \tilde{\delta} \mathbf{D})^{-1} \mathbf{A} \tilde{\mathbf{T}}. \quad (22)$$

Then, in Table I we define the deterministic quantities that will be extensively used in the remainder of this paper. Also, we denote by $\mathbf{a}_\ell$ the ℓ th column of matrix $\mathbf{A}$ and call $\tilde{t}_\ell$, $\tilde{d}_\ell$ and $\tilde{d}_\ell$ the ℓ th diagonal elements of matrices $\tilde{\mathbf{T}}$, $\mathbf{D}$ and $\tilde{\mathbf{D}}$, respectively.

B. A useful and new result

The following theorem represents a major contribution of this work as it extends the results in [13]. This theorem is required to cope with the channel model in (7) and forms the mathematical basis for the subsequent large system analysis of RZF precoding. Particularly, it provides deterministic

equivalents of quadratic forms and normalized traces involving two occurrences of the resolvent matrix $\mathbf{Q}$. This problem was addressed in [8], [26] for various random matrix models associated with centered random matrices, and recently with non-centered random matrices [13]. This latter scenario is much more complicated and was only handled in [13] for specific functionals, as discussed later on.

Theorem 1. *Let $\mathbf{C} \in \mathbb{C}^{N \times N}$ be a sequence of deterministic matrices whose spectral norms are uniformly bounded in N . Let $\mathbf{v} \in \mathbb{C}^N$ be a sequence of deterministic vectors whose euclidean norms are uniformly bounded in N . Assume that $\theta(\mathbf{v}, \mathbf{C})$ and $\chi(\mathbf{C})$ are defined as follows:*

$$\theta(\mathbf{v}, \mathbf{C}) = \mathbb{E} [\mathbf{v}^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (23)$$

and

$$\chi(\mathbf{C}) = \mathbb{E} \left[\frac{1}{N} \text{Tr} (\mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q}) \right]. \quad (24)$$

Then, we have that:

$$\begin{aligned} \theta(\mathbf{v}, \mathbf{C}) &= \mathbf{v}^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{v} \\ &+ \mathbf{v}^H \mathbf{T} \mathbf{A} \tilde{\mathbf{D}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-2} \mathbf{A}^H \mathbf{T} \mathbf{v} \left(\frac{\vartheta(\mathbf{C})(1-F) + \vartheta F(\mathbf{C})}{\Delta} \right) \\ &+ \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \left(\frac{F(\mathbf{C})(1-F)}{\Delta} + \frac{\lambda^2 \vartheta(\mathbf{C}) \tilde{\vartheta}}{\Delta} \right) + \mathcal{O}(N^{-\frac{1}{2}}) \end{aligned} \quad (25)$$

and

$$\chi(\mathbf{C}) = \frac{(1-F)\vartheta(\mathbf{C})}{\Delta} + \frac{\vartheta F(\mathbf{C})}{\Delta} + \mathcal{O}(N^{-\frac{1}{2}}) \quad (26)$$

with $F(\mathbf{C})$ and $\vartheta(\mathbf{C})$ given by

$$F(\mathbf{C}) = \frac{1}{N} \text{Tr} \left(\tilde{\mathbf{D}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-2} \mathbf{A}^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{A} \right) \quad (27)$$

$$\vartheta(\mathbf{C}) = \frac{1}{N} \text{Tr} (\mathbf{D} \mathbf{T} \mathbf{C} \mathbf{T}). \quad (28)$$

Proof. The proof is given in Appendix A and unfolds using the same approach in [13], which basically consists in replacing (by using the resolvent identity) one occurrence of the random matrix $\mathbf{Q}$ in (23) and (24) with $\mathbf{T}$. A sum of different random quantities is thus obtained. Each quantity is handled separately using random matrix theory tools. In doing so, however, we end up with expressions that are much more involved of those in [13]. $\square$

As mentioned above, Theorem 1 is not just an extension of the results in [13] but also a key tool for the subsequent large system analysis. As detailed in Appendix B, the asymptotic analysis of the SINR given in (5) requires not only to consider $\mathbf{v} = \mathbf{a}_\ell$ for any $\ell \in \{1, \dots, K\}$ and $\mathbf{C} = \mathbf{D}$ as done in [13] but also $\mathbf{v} = \mathbf{a}_\ell$ and $\mathbf{C} = \tilde{\mathbf{C}}_\ell = \sum_{k \neq \ell} \alpha_k \mathbf{a}_k \mathbf{a}_k^H$ for any $\ell \in \{1, \dots, K\}$ and any scalar coefficients $\{\alpha_k; k = 1, \dots, K\}$. For the reader convenience and to facilitate the derivation in Appendix B, both cases are addressed in the following two corollaries.

Corollary 1. *If $\mathbf{C} = \mathbf{D}$ and $\mathbf{v} = \mathbf{a}_\ell$ for some $\ell \in \{1, \dots, K\}$, then (25) and (26) simplify to*

$$\begin{aligned} \theta(\mathbf{a}_\ell, \mathbf{D}) &= \frac{(1-F)}{\Delta} \mathbf{a}_\ell^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_\ell \\ &+ \frac{\vartheta}{\Delta} \mathbf{a}_\ell^H \mathbf{T} \mathbf{A} \tilde{\mathbf{D}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-2} \mathbf{A}^H \mathbf{T} \mathbf{a}_\ell + \mathcal{O}(N^{-\frac{1}{2}}) \end{aligned} \quad (29)$$

$$= \frac{1-F}{\Delta} \left(1 + \delta \tilde{d}_\ell \right)^2 \tilde{\gamma}_\ell + \frac{\vartheta}{\Delta} \Lambda_\ell + \mathcal{O}(N^{-\frac{1}{2}}) \quad (30)$$

where $\tilde{\gamma}_\ell$ is given in Table I, $\{\tilde{t}_\ell\}_{\ell=1}^K$ are the diagonal elements of $\tilde{\mathbf{T}}$ and

$$\begin{aligned} \Lambda_\ell &= \lambda^2 \left(1 + \delta \tilde{d}_\ell \right)^2 \left([\tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}}]_{\ell\ell} - \tilde{t}_\ell^2 \tilde{d}_\ell \right) \\ &+ \frac{\tilde{d}_\ell}{\left(1 + \delta \tilde{d}_\ell \right)^2} \left| \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell \right|^2. \end{aligned} \quad (31)$$

Also, we have that

$$\chi(\mathbf{D}) = \frac{\vartheta}{\Delta} + \mathcal{O}(N^{-\frac{1}{2}}). \quad (32)$$

Proof: If $\mathbf{C} = \mathbf{D}$ and $\mathbf{v} = \mathbf{a}_\ell$ then $\vartheta(\mathbf{C}) = \vartheta$ and $F(\mathbf{C}) = F$ as defined in Table I. To prove (30), we rely on the following relation between $\tilde{\mathbf{T}}$ and $\mathbf{T}$ which can be found in [13, Eq. 3.12]:

$$\lambda \tilde{\mathbf{T}} = (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} - (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} \mathbf{A}^H \mathbf{T} \mathbf{A} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} \quad (33)$$

or, equivalently,

$$\lambda (\mathbf{I}_K + \delta \tilde{\mathbf{D}}) \tilde{\mathbf{T}} (\mathbf{I}_K + \delta \tilde{\mathbf{D}}) = (\mathbf{I}_K + \delta \tilde{\mathbf{D}}) - \mathbf{A}^H \mathbf{T} \mathbf{A}. \quad (34)$$

The following identity, whose proof can be found in [13, pag. 48], is also needed

$$\begin{aligned} (\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2 &= \lambda^2 \tilde{t}_\ell^2 \left(1 + \delta \tilde{d}_\ell \right)^4 - \lambda \tilde{t}_\ell \left(1 + \delta \tilde{d}_\ell \right)^3 \\ &+ \left(1 + \delta \tilde{d}_\ell \right) \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell. \end{aligned} \quad (35)$$

By using (33), we obtain:

$$\begin{aligned} \mathbf{a}_\ell^H \mathbf{T} \mathbf{A} \tilde{\mathbf{D}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-2} \mathbf{A}^H \mathbf{T} \mathbf{a}_\ell \\ = \mathbf{e}_\ell^T \mathbf{A}^H \mathbf{T} \mathbf{A} \tilde{\mathbf{D}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-2} \mathbf{A}^H \mathbf{T} \mathbf{A} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-1} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right) \mathbf{e}_\ell \end{aligned} \quad (36)$$

$$\begin{aligned} &= \frac{\tilde{d}_\ell}{1 + \delta \tilde{d}_\ell} \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell \\ &- \lambda \mathbf{e}_\ell^T \mathbf{A}^H \mathbf{T} \mathbf{A} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-1} \tilde{\mathbf{D}} \tilde{\mathbf{T}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right) \mathbf{e}_\ell \end{aligned} \quad (37)$$

$$= \lambda (1 + \delta \tilde{d}_\ell) \left(\lambda (1 + \delta \tilde{d}_\ell) [\tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}}]_{\ell\ell} - \tilde{t}_\ell \tilde{d}_\ell \right) + \frac{\tilde{d}_\ell}{1 + \delta \tilde{d}_\ell} \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell \quad (38)$$

which (35) allows to rewrite as

$$\mathbf{a}_\ell^H \mathbf{T} \mathbf{A} \tilde{\mathbf{D}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right)^{-2} \mathbf{A}^H \mathbf{T} \mathbf{a}_\ell = \Lambda_\ell \quad (39)$$

with Λ_ℓ given by (31). From the identity in (22), we have that:

$$\mathbf{a}_\ell^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_\ell = \left(1 + \delta \tilde{d}_\ell \right)^2 \left[\tilde{\mathbf{T}} \mathbf{A}^H \mathbf{D} (\mathbf{I}_N + \delta \tilde{\mathbf{D}})^{-2} \mathbf{A} \tilde{\mathbf{T}} \right]_{\ell\ell} \quad (40)$$

$$= \left(1 + \delta \tilde{d}_\ell \right)^2 \tilde{\gamma}_\ell. \quad (41)$$

By plugging (39) and (41) into (29), we obtain (30). ■

Corollary 2. *If $\mathbf{v} = \mathbf{a}_\ell$ for some $\ell \in \{1, \dots, K\}$ and $\mathbf{C} = \bar{\mathbf{C}}_\ell = \sum_{k \neq \ell} \alpha_k \mathbf{a}_k \mathbf{a}_k^H$ where $\{\alpha_k; k = 1, \dots, K\}$ is a deterministic sequence that is bounded uniformly in K and N , we obtain:*

$$\begin{aligned} \theta(\mathbf{a}_\ell, \bar{\mathbf{C}}_\ell) &= \left(\lambda^2 (1 + \delta \tilde{d}_\ell)^2 \phi_\ell - \lambda^2 \tilde{t}_\ell^2 (1 + \delta \tilde{d}_\ell)^4 \alpha_\ell \right) \\ &+ \Lambda_\ell \left(\frac{(1-F)}{\Delta} \vartheta(\bar{\mathbf{C}}_\ell) + \frac{\vartheta}{\Delta} F(\bar{\mathbf{C}}_\ell) \right) \\ &+ (1 + \delta \tilde{d}_\ell)^2 \tilde{\gamma}_\ell \left(\frac{1-F}{\Delta} F(\bar{\mathbf{C}}_\ell) + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \vartheta(\bar{\mathbf{C}}_\ell) \right) + O(N^{-\frac{1}{2}}) \end{aligned} \quad (42)$$

where we have defined $\phi_\ell = [\Phi]_{\ell\ell}$ with

$$\Phi = \tilde{\mathbf{T}} \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right) \text{diag} \{ \alpha_l \}_{l=1}^K \left(\mathbf{I}_K + \delta \tilde{\mathbf{D}} \right) \tilde{\mathbf{T}}. \quad (43)$$

Moreover, $F(\bar{\mathbf{C}}_\ell)$ and $\vartheta(\bar{\mathbf{C}}_\ell)$ simplify as

$$\begin{aligned} F(\bar{\mathbf{C}}_\ell) &= \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l \phi_\ell - \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l \alpha_l \tilde{t}_l^2 (1 + \delta \tilde{d}_l)^2 \\ &+ \frac{1}{N} \sum_{l=1}^K \tilde{d}_l \alpha_l \frac{|\mathbf{a}_l^H \mathbf{T} \mathbf{a}_\ell|^2}{(1 + \delta \tilde{d}_l)^2} \end{aligned} \quad (44)$$

and

$$\vartheta(\bar{\mathbf{C}}_\ell) = \frac{1}{N} \sum_{k \neq \ell} \alpha_k (1 + \delta \tilde{d}_k)^2 \tilde{\gamma}_k. \quad (45)$$

Proof: By applying Theorem 1, we obtain:

$$\begin{aligned} \theta(\mathbf{a}_\ell, \bar{\mathbf{C}}_\ell) &= \mathbf{a}_\ell^H \mathbf{T} \sum_{k \neq \ell} \alpha_k \mathbf{a}_k \mathbf{a}_k^H \mathbf{T} \mathbf{a}_\ell \\ &+ \mathbf{a}_\ell^H \mathbf{T} \tilde{\mathbf{A}} \tilde{\mathbf{D}} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-2} \mathbf{A}^H \mathbf{T} \mathbf{a}_\ell \left(\frac{1-F}{\Delta} \vartheta(\bar{\mathbf{C}}_\ell) + \frac{\vartheta}{\Delta} F(\bar{\mathbf{C}}_\ell) \right) \\ &+ \mathbf{a}_\ell^H \mathbf{T} \tilde{\mathbf{D}} \mathbf{T} \mathbf{a}_\ell \left(\frac{1-F}{\Delta} F(\bar{\mathbf{C}}_\ell) + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \vartheta(\bar{\mathbf{C}}_\ell) \right) + O(N^{-\frac{1}{2}}). \end{aligned} \quad (46)$$

By using the same techniques as in the proof of Corollary 1, we obtain

$$\begin{aligned} \mathbf{a}_\ell^H \mathbf{T} \sum_{k \neq \ell} \alpha_k \mathbf{a}_k \mathbf{a}_k^H \mathbf{T} \mathbf{a}_\ell &= \lambda^2 (1 + \delta \tilde{d}_\ell)^2 \phi_\ell \\ &+ \alpha_\ell (1 + \delta \tilde{d}_\ell) \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell - \lambda \alpha_\ell (1 + \delta \tilde{d}_\ell)^3 \tilde{t}_\ell - \alpha_\ell (\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2 \end{aligned} \quad (47)$$

$$= \lambda^2 (1 + \delta \tilde{d}_\ell)^2 \phi_\ell - \alpha_\ell \lambda^2 \tilde{t}_\ell^2 (1 + \delta \tilde{d}_\ell)^4. \quad (48)$$

By using (39) and (41), $F(\bar{\mathbf{C}}_\ell)$ reduces to (up to an error $O(N^{-1})$)

$$\begin{aligned} F(\bar{\mathbf{C}}_\ell) &= \frac{1}{N} \sum_{k=1}^K \lambda^2 \alpha_k (1 + \delta \tilde{d}_k)^2 [\tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}}]_{kk} \\ &+ \frac{1}{N} \sum_{k=1}^K \alpha_k \tilde{d}_k \frac{(\mathbf{a}_k^H \mathbf{T} \mathbf{a}_k)^2}{(1 + \delta \tilde{d}_k)^2} - \frac{1}{N} \sum_{k=1}^K \lambda^2 \tilde{d}_k \alpha_k \tilde{t}_k^2 (1 + \delta \tilde{d}_k)^2 \end{aligned} \quad (49)$$

whereas takes $\vartheta(\bar{\mathbf{C}}_\ell)$ the form in (45). ■

As those in Theorem 1, the expressions provided in Corollaries 1 and 2 are rather complicated and do not allow to get any interesting insight. However, this is not of primary importance for our purpose. What is important is that they are eventually instrumental to get fairly simple and illustrative asymptotic approximations of the SINR under different operating conditions.

C. Asymptotic Analysis

Theorem 1 plays a key role in proving the following theorem, which summarizes one of the major results of this work.

Theorem 2. *Let Assumptions 1 – 3 hold true. Then, we have that $\max_k |\gamma_k - \bar{\gamma}_k| \rightarrow 0$ with*

$$\bar{\gamma}_k = \frac{p_k (1 - \lambda \tilde{t}_k)^2}{\underbrace{\tilde{s}'_k}_{\text{non-coherent interference}} + \underbrace{\lambda^2 ([\tilde{\mathbf{T}} \tilde{\mathbf{P}} \tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2)}_{\text{coherent interference}} + \bar{\psi} \frac{\sigma^2}{N P_T}} \quad (50)$$

where $\tilde{s}'_k$ is given by

$$\begin{aligned} \tilde{s}'_k &= \lambda^2 [\tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}}]_{kk} \left(\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l + \frac{\vartheta}{\Delta} \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}} \tilde{\mathbf{P}} \tilde{\mathbf{T}}]_{ll} \right) \\ &+ \tilde{\gamma}_k \left(\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}} \tilde{\mathbf{P}} \tilde{\mathbf{T}}]_{ll} + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l \right). \end{aligned} \quad (51)$$

Also, we have that

$$\begin{aligned} \bar{\psi} &= \frac{1}{K} \text{Tr} \left(\mathbf{P} \tilde{\mathbf{T}} \mathbf{A}^H (\mathbf{I}_N + \delta \tilde{\mathbf{D}})^{-2} \mathbf{A} \tilde{\mathbf{T}} \right) \\ &+ \frac{\lambda^2}{K} \text{Tr} \left(\mathbf{P} \tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}} \right) \left(\frac{1-F}{\Delta} \alpha + \frac{\vartheta}{\Delta} V \right) \\ &+ \frac{1}{K} \sum_{\ell=1}^K p_\ell \tilde{\gamma}_\ell \left(\frac{1-F}{\Delta} V + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \alpha \right). \end{aligned} \quad (52)$$

Proof: The proof is very much involved and is given in Appendix B. It basically relies on results in random matrix theory [13], [14] as well as on those provided in Corollaries 1 and 2. ■

The asymptotic expressions (50) and (51) provide some insights into the basic behaviour of large-scale MU-MIMO systems with RZF under Rician fading channels. Following [27], the first term in the denominator is referred to as non-coherent interference because it vanishes with $1/N$ as $N \rightarrow \infty$ and K is kept fixed [27]. Accordingly, the second term $\lambda^2 ([\tilde{\mathbf{T}} \tilde{\mathbf{P}} \tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2)$ is called coherent interference since it maintains constant with respect to N as the signal term. This is a consequence of the intracell interference generated by the LoS components, as it follows from (16).

We are ultimately interested in the individual rates $\{r_k\}$ and the ergodic sum rate r_E . Since the logarithm is a continuous function, by applying the continuous mapping theorem and the dominated convergence theorem, from the almost sure

convergence results of Theorem 2 it follows that $r_k - \bar{r}_k \rightarrow 0$ almost surely with [8]

$$\bar{r}_k = \log_2(1 + \bar{\gamma}_k). \quad (53)$$

An approximation of r_E is obtained as follows [8]

$$\bar{r}_E = \sum_{k=1}^K \log_2(1 + \bar{\gamma}_k) \quad (54)$$

such that $\frac{1}{K}(r_E - \bar{r}_E) \rightarrow 0$ holds true almost surely. The asymptotic approximation of $\bar{r}_E$ will be shown to be very tight, by means of numerical results in Section IV, even for systems with finite dimensions. This means that, when applied to practical networks, such approximations can be used to evaluate the spectral efficiency of the network without to carry out extensive Monte Carlo simulations, which require to compute the precoding scheme in (2) (and the corresponding SINR in (5)) for any given realization of channel vectors $\{\mathbf{h}_k; k = 1, \dots, K\}$. This requires to compute the inverse of a matrix of size $\min(N, K)$, which becomes computationally demanding when N, K increase as envisioned in large-scale MU-MIMO systems. Moreover, these operations must be performed over a sufficiently large number of channel realizations to obtain a good estimate of the expected spectral efficiency of the system. All this makes the complexity incurred by the Monte Carlo methodology prohibitively high in large-scale MU-MIMO systems. On the other hand, the methodology based on the asymptotic analysis allows to evaluate the spectral efficiency of the system by only using the macroscopic statistics of the channels; that is, there is no need to generate a large number of channel vectors and to take an average over all these realizations. This allows a significant computational saving. In addition to all this, evaluating the performance of a system with a Monte Carlo methodology does not allow to get any analytical insight into the system itself. This is why asymptotic analyses are abundant in communication theory.

To get further insights from the asymptotic expression provided in Theorem 2, we now look to the the limiting case in which $N \rightarrow \infty$ with $K/N \rightarrow 0$.¹

Corollary 3. *If $N \rightarrow \infty$ with $K/N \rightarrow 0$ and there exists i, k such that $i \neq k$ and $\mathbf{a}_k^H \mathbf{a}_i \not\rightarrow 0$, then, under Assumptions 2 and 3, we have that $\max_k |\gamma_k - \bar{\gamma}_k| \rightarrow 0$ with:*

$$\bar{\gamma}_k = \frac{p_k(1 - \lambda \tilde{t}_k)^2}{\underbrace{\lambda^2([\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2)}_{\text{coherent interference}}} \quad (55)$$

with $\tilde{\mathbf{T}}$ now given by

$$\tilde{\mathbf{T}} = \left(\lambda \mathbf{I}_K + \left(\frac{1}{N} \text{Tr}(\mathbf{D}) \right) \tilde{\mathbf{D}} + \mathbf{A}^H \mathbf{A} \right)^{-1} \quad (56)$$

and $\{\tilde{t}_k; k = 1, \dots, K\}$ denote its diagonal elements.

¹The limiting case $N \rightarrow \infty$ and $K/N \rightarrow 0$ can be retrieved from the results of Theorem 2 because in all approximations (including variance control or mean approximation), the error can be bounded by $C/N^\alpha (K/N)^\beta$ for some constant C , and integers α and β . This ensures that the error remains bounded as $K/N \rightarrow 0$.

Proof: The proof follows from the results of Theorem 2 by noticing that if $K/N \rightarrow 0$, $\delta - \frac{1}{N\lambda} \text{Tr}(\mathbf{D}) \rightarrow 0$, $F \rightarrow 0$, $V \rightarrow 0$, $\tilde{\vartheta} \rightarrow 0$ and $\alpha - \frac{1}{N\lambda^2} \text{Tr}(\mathbf{D}) \rightarrow 0$. ■

The above corollary shows that when N grows at a faster rate than K the asymptotic interference towards UE k does not necessarily vanish as it depends on the LoS components $\{\mathbf{a}_i; i = 1, \dots, K\}$ through $\mathbf{T}$ given in (16). In particular, unlike Rayleigh fading, it depends on the inner products between the vector $\mathbf{a}_k$ and all other vectors $\mathbf{a}_i$ with $i \neq k$. If the BS is equipped with a uniform linear array (ULA) and LoS vectors $\mathbf{a}_k$ and $\mathbf{a}_i$ are either aligned in the complex plane or have an angular difference that scales as $1/N^\alpha$ with $\alpha \geq 1$, then $\mathbf{a}_k^H \mathbf{a}_i$ (or equivalently $\mathbf{h}_k^H \mathbf{h}_i/N$) does not vanish asymptotically. Both cases belong to the category of scenarios for which the *favorable propagation conditions* are not satisfied [28].

Consider now a system in which $\mathbf{a}_k^H \mathbf{a}_i \rightarrow 0 \forall i \neq k$, which implies that $\mathbf{h}_k^H \mathbf{h}_i/N \rightarrow 0 \forall i \neq k$. This means that UEs satisfy asymptotically favorable propagation conditions [28]. Then, we have that:

Corollary 4. *If $N \rightarrow \infty$ with $K/N \rightarrow 0$ and $\mathbf{a}_k^H \mathbf{a}_i \rightarrow 0 \forall i \neq k$, then we have that*

$$\max_k \sum_{i=1, i \neq k}^K p_i |\mathbf{h}_k^H \mathbf{g}_i|^2 \rightarrow 0. \quad (57)$$

Proof: The proof easily follows from noticing that under favorable propagation conditions, i.e., $\mathbf{a}_k^H \mathbf{a}_i \rightarrow 0 \forall i \neq k$, the matrix $\tilde{\mathbf{T}}$ becomes asymptotically diagonal such that

$$[\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2 \rightarrow 0. \quad (58)$$

In agreement with [19], [28], the above corollary shows that if the MIMO Rician fading channel results in favorable propagations, then the interference vanishes as N grows unbounded, and consequently the ergodic sum rate grows unbounded, as $N \rightarrow \infty$. In practice, this can only be achieved if some UEs are dropped from service [29].

D. Case Studies

Further illustrative case studies are considered next to get additional insights into the effect of system parameters. To begin with, we assume that the BS antennas are uncorrelated. This is equivalent to assuming that $\Theta = \mathbf{I}_N$. Then, we have that:

Corollary 5. *Let Assumptions 1 and 3 hold true. If $\Theta = \mathbf{I}_N$, then $\max_k |\gamma_k - \bar{\gamma}_k| \rightarrow 0$ with:*

$$\bar{\gamma}_k = \frac{p_k(1 - \lambda \tilde{t}_k)^2}{\underbrace{\lambda^2([\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2)}_{\text{coherent interference}} + \underbrace{\bar{s}'_k}_{\text{non-coherent interference}} + \bar{\psi} \frac{\sigma^2}{N P_T}} \quad (59)$$

where

$$\bar{\psi} = \frac{\vartheta}{\Delta} \frac{\lambda^2}{K} \text{Tr}(\mathbf{P}\tilde{\mathbf{T}}\mathbf{D}\tilde{\mathbf{T}}) + \frac{1-F}{\Delta} \sum_{\ell=1}^K \tilde{\gamma}_\ell p_\ell \quad (60)$$

and

$$\begin{aligned} \bar{s}'_k &= \lambda^2 [\tilde{\mathbf{T}}\tilde{\mathbf{D}}\tilde{\mathbf{T}}]_{kk} \left(\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l + \frac{\vartheta}{\Delta} \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}}\tilde{\mathbf{P}}\tilde{\mathbf{T}}]_{ll} \right) \\ &+ \tilde{\gamma}_k \left(\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}}\tilde{\mathbf{P}}\tilde{\mathbf{T}}]_{ul} + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l \right) \end{aligned} \quad (61)$$

with $\tilde{\gamma}_l = \frac{[\tilde{\mathbf{T}}\mathbf{A}^H\mathbf{A}\tilde{\mathbf{T}}]_{ll}}{(1+\tilde{\delta})^2}$. If furthermore $\mathbf{a}_k^H \mathbf{a}_i = 0$, the matrix $\tilde{\mathbf{T}}$ becomes diagonal and thus the coherent interference $[\tilde{\mathbf{T}}\tilde{\mathbf{P}}\tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2 = 0$ vanishes.

Proof: The proof follows by noting that when $\mathbf{D} = \mathbf{I}_N$, $\alpha = \vartheta$ and $V = F$. Replacing these quantities into the expressions of Theorem 2 yields (60). ■

Consider now the case for which only the channel of the UE of interest, i.e, UE k , is characterized by a Rician fading channel, whereas a Rayleigh fading channel model is valid for all other UEs with indexes $i \neq k$. Assume also that $\|\mathbf{a}_k\|^2 = \beta_k \frac{\rho}{1+\rho}$. Then, we have that $[\tilde{\mathbf{D}}]_{k,k} = \frac{\beta_k}{1+\rho}$ and $[\tilde{\mathbf{D}}]_{i,i} = \beta_i$ for $i \neq k$, which is slightly different from the original setting described by (9). Under the above circumstances, the following result is found:

Corollary 6. *Let Assumptions 1 and 3 hold true. If $\Theta = \mathbf{I}_N$, $\|\mathbf{a}_k\|^2 = \frac{\beta_k \rho}{\rho+1}$ and no LoS component is present for all other UEs with indexes $i \neq k$, then $\max_k |\gamma_k - \bar{\gamma}_k| \rightarrow 0$ with:*

$$\bar{\gamma}_k = \frac{p_k \left(1 - \frac{1}{1 + \frac{\beta_k}{\lambda(1+\tilde{\delta})}}\right)^2 \left(1 - \frac{1}{N} \sum_{l=1}^K \frac{\beta_l^2}{(\lambda(1+\tilde{\delta}) + \beta_l)^2}\right)}{\frac{1}{N} \sum_{l=1}^K p_l \beta_l \frac{(\lambda(1+\tilde{\delta}) + \beta_k)^{-2} + \frac{\sigma^2 \lambda^2}{P_T K} (1+\tilde{\delta})^{-2}}{\left(1 + \frac{\beta_l}{\lambda(1+\tilde{\delta})}\right)^2}} \quad (62)$$

where $\tilde{\delta}$ is the unique solution of the following equation:

$$\tilde{\delta} = \frac{1}{N} \sum_{k=1}^K \frac{\beta_k (1 + \tilde{\delta})}{\lambda(1 + \tilde{\delta}) + \beta_k}. \quad (63)$$

Proof: By substituting the expressions of $\mathbf{A}$ and $\tilde{\mathbf{D}}$ into (16) and (17), from (14) and (15) (using the fact that $\mathbf{A}$ has rank 1) we get (63) and

$$\delta = \frac{1}{\lambda(1 + \tilde{\delta})}. \quad (64)$$

Also, it is found that $\tilde{t}_k = \frac{1}{\lambda(1 + \frac{\beta_k \delta}{1+\rho}) + \frac{\beta_k \rho}{(1+\rho)(1+\tilde{\delta})}} = \frac{1}{\lambda + \frac{\beta_k}{1+\tilde{\delta}}}$ and $\tilde{t}_{ii} = \frac{1}{\lambda + \frac{\beta_i}{1+\tilde{\delta}}}$ for $i \neq k$. Since $\mathbf{A}$ has finite rank, $F \rightarrow 0$, $\frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l \rightarrow 0$ while $\tilde{\gamma}_k = \frac{\beta_k \rho}{1+\rho} \frac{\tilde{t}_k^2}{(1+\tilde{\delta})^2}$. Moreover, it follows that $\mathbf{D} = \mathbf{I}_N$ and $\vartheta = \delta^2 + \mathcal{O}(N^{-1})$.

Using all the above results, we can simplify the interference $\bar{s}_k = \lambda^2 ([\tilde{\mathbf{T}}\tilde{\mathbf{P}}\tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2) + \bar{s}'_k$ as:

$$\begin{aligned} \bar{s}_k &= \left(\frac{\lambda^2 \delta^2 \tilde{t}_k^2 \beta_k}{(1+\rho)\Delta} + \frac{\tilde{\gamma}_k}{\Delta} \right) \frac{1}{N} \sum_{\ell \neq k} p_\ell \beta_\ell \tilde{t}_\ell^2 + \mathcal{O}(N^{-1}) \\ &= \left(\frac{\tilde{t}_k^2}{(1+\tilde{\delta})^2} \frac{\beta_k}{1+\rho} + \tilde{t}_k^2 \frac{\beta_k \rho}{(1+\rho)(1+\tilde{\delta})^2} \right) \frac{1}{N} \sum_{\ell \neq k} \frac{p_\ell \beta_\ell \tilde{t}_\ell^2}{\Delta} + \mathcal{O}(N^{-1}) \\ &= \frac{\beta_k \tilde{t}_k^2}{(1+\tilde{\delta})^2} \frac{1}{N} \sum_{l=1}^K \frac{p_l \beta_l \tilde{t}_l^2}{\Delta} + \mathcal{O}(N^{-1}) \\ &= \frac{\beta_k \tilde{t}_k^2}{(1 - \lambda^2 \vartheta \tilde{\vartheta}) (1 + \tilde{\delta})^2} \frac{1}{N} \sum_{l=1}^K \frac{p_l \beta_l}{\left(1 + \frac{\beta_l}{\lambda(1+\tilde{\delta})}\right)^2} + \mathcal{O}(N^{-1}). \end{aligned} \quad (65)$$

By using the results above, we can also prove that

$$\bar{\psi} = \frac{\lambda^2}{(1 - \lambda^2 \vartheta \tilde{\vartheta}) (1 + \tilde{\delta})^2} \frac{N}{K} \frac{1}{N} \sum_{l=1}^K \frac{p_l \beta_l}{\left(1 + \frac{\beta_l}{\lambda(1+\tilde{\delta})}\right)^2}. \quad (66)$$

By substituting (65) and (66) into (59) yields (62), after some standard calculus. ■

The results of Corollary 6 coincide with those obtained for the case in which all UEs experience Rayleigh fading propagations. This means that the asymptotic expression of the SINR for a given UE k is independent from its own channel model if all the other UEs are affected by Rayleigh fading.

To gain further insights into the impact of the Rician factor ρ , assume that the channel can be simply modelled as $\Theta = \mathbf{I}_N$, $\tilde{\mathbf{D}} = \frac{\beta}{1+\rho} \mathbf{I}_K$ and $\mathbf{A}^H \mathbf{A} = \frac{\rho \beta}{1+\rho} \mathbf{I}_K$. In this case, the following result holds true:

Corollary 7. *Let Assumption 1 holds true. Assume furthermore that $\tilde{\mathbf{D}} = \frac{\beta}{1+\rho} \mathbf{I}_K$, $\mathbf{A}^H \mathbf{A} = \frac{\rho \beta}{1+\rho} \mathbf{I}_K$ and $\Theta = \mathbf{I}_N$. Let $\tilde{\delta}$ be the unique positive solution to the following third order equation in x*

$$\begin{aligned} &\lambda x^3 + x^2 \left(2\lambda + \frac{\beta}{1+\rho} \frac{N-K}{N} \right) + x \left(\lambda + \frac{\beta}{1+\rho} \frac{N-2K}{N} + \frac{\rho \beta}{1+\rho} \right) \\ &- \frac{K}{N} \frac{\beta}{1+\rho} = 0. \end{aligned} \quad (67)$$

Define ϑ as:

$$\begin{aligned} \vartheta &= \frac{1}{\lambda \beta} \left[\frac{(1+\rho)\tilde{\delta}}{(1+\tilde{\delta})} + \frac{N-K}{N\lambda} \frac{\beta}{1+\tilde{\delta}} - \frac{\rho N}{K} \frac{(1+\rho)\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right. \\ &\quad \left. - \frac{N-K}{K\lambda} \frac{\rho \beta \tilde{\delta}^2}{(1+\tilde{\delta})^3} \right] \end{aligned} \quad (68)$$

and

$$\Delta = \left(1 - \frac{N\rho}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right)^2 - \lambda^2 \vartheta \frac{N}{K} \tilde{\delta}^2. \quad (69)$$

Then, $\max_k |\gamma_k - \bar{\gamma}_k| \rightarrow 0$ with:

$$\bar{\gamma}_k = \frac{p_k \left(1 - \lambda \tilde{\delta} \frac{N}{K} \left(\frac{1+\rho}{\beta} \right) \right)^2}{\bar{s}_k + \bar{\psi} \frac{\sigma^2}{N P_T}} \quad (70)$$

where

$$\bar{s}_k = \frac{\lambda^2}{N} \tilde{\delta}^2 \text{Tr}(\mathbf{P}) \left(\frac{1+\rho}{\beta} \right)^2 \left(\frac{N}{K} \right)^3 \left(\frac{1}{\Delta} - 1 \right) \quad (71)$$

and

$$\bar{\psi} = \left(\frac{1 - \frac{N\rho}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2}}{\Delta} - 1 \right) \frac{1+\rho}{\beta} \frac{N}{K} \frac{1}{K} \text{Tr}(\mathbf{P}). \quad (72)$$

Proof: We start by proving (67). For the specific considered case, $\tilde{\delta}$ simplifies to

$$\tilde{\delta} = \frac{\beta}{N(1+\rho)} \text{Tr} \left(\lambda(1+\delta) \frac{\beta}{1+\rho} \mathbf{I}_K + \frac{\rho\beta}{(1+\rho)(1+\tilde{\delta})} \mathbf{I}_K \right)^{-1} \quad (73)$$

$$= \frac{\frac{K}{N} \frac{\beta}{1+\rho}}{\lambda + \lambda\delta \frac{\beta}{1+\rho} + \frac{\rho\beta}{(1+\rho)(1+\tilde{\delta})}}. \quad (74)$$

The right-hand-side of (73) can be rewritten as:

$$\tilde{\delta} = \left(1 + \frac{\delta\beta}{1+\rho} \right)^{-1} (1+\tilde{\delta}) \frac{\beta}{1+\rho} \times \left[\frac{1}{N} \text{Tr} \left(\lambda(1+\tilde{\delta}) \mathbf{I}_N + \frac{\mathbf{A}\mathbf{A}^H}{1 + \frac{\delta\beta}{1+\rho}} \right)^{-1} - \frac{N-K}{N\lambda(1+\tilde{\delta})} \right] \quad (75)$$

$$= \frac{(1+\tilde{\delta})\beta}{1+\rho+\delta\beta} \left(\delta - \frac{N-K}{N\lambda(1+\tilde{\delta})} \right) \quad (76)$$

from which we obtain

$$\beta\delta = (1+\rho)\tilde{\delta} + \frac{\beta}{\lambda} \frac{N-K}{N}. \quad (77)$$

By plugging (77) into (74), we obtain (67) after some standard calculus. Once the equation involving $\tilde{\delta}$ is established, the expressions of the interference and $\bar{\psi}$ follow after tedious but straightforward calculations. To this end, we need to compute the asymptotic expressions of Δ and ϑ as a function β , $\frac{N}{K}$ and ρ . Let us start with simplifying F . Since $\tilde{\mathbf{T}}$ is proportional to identity, and using the fact that $\tilde{\delta} = \frac{1}{N} \text{Tr}(\tilde{\mathbf{D}}\tilde{\mathbf{T}}) = \frac{\beta}{1+\rho} \frac{1}{N} \text{Tr}(\tilde{\mathbf{T}})$, all elements of $\tilde{\mathbf{T}}$ are equal to $\tilde{t}_k = \frac{N}{K} \frac{1+\rho}{\beta} \tilde{\delta}$. Therefore, F simplifies to

$$F = \frac{N\rho}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2}. \quad (78)$$

Following the same arguments, $\tilde{\vartheta}$ can be rewritten as:

$$\tilde{\vartheta} = \frac{N}{K} \tilde{\delta}^2. \quad (79)$$

To proceed further, we observe that multiplying the left and right hand sides of the following relation

$$\mathbf{T} \left(\lambda(1+\tilde{\delta}) \mathbf{I}_N + \mathbf{A} \left(\mathbf{I}_K + \delta\tilde{\mathbf{D}} \right)^{-1} \mathbf{A}^H \right) = \mathbf{I} \quad (80)$$

with $\mathbf{T}$ yields

$$\lambda(1+\tilde{\delta}) \mathbf{T}^2 + \mathbf{T}\mathbf{A} \left(\mathbf{I}_K + \delta\tilde{\mathbf{D}} \right)^{-1} \mathbf{A}^H \mathbf{T} = \mathbf{T}. \quad (81)$$

Using the relation $\mathbf{T}\mathbf{A} \left(\mathbf{I}_K + \delta\tilde{\mathbf{D}} \right)^{-1} = \left(\mathbf{I}_N + \delta\tilde{\mathbf{D}} \right)^{-1} \mathbf{A}\tilde{\mathbf{T}}$, we obtain:

$$\frac{1}{N} \text{Tr}(\mathbf{T}^2) \lambda(1+\tilde{\delta}) + \frac{1}{(1+\tilde{\delta})^2} \frac{\beta\rho}{1+\rho} \left(1 + \frac{\delta\beta}{1+\rho} \right) \frac{1}{N} \text{Tr}(\tilde{\mathbf{T}}) = \frac{1}{N} \text{Tr}(\mathbf{T}). \quad (82)$$

Hence, we have that

$$\begin{aligned} \frac{1}{N} \text{Tr}(\mathbf{T}^2) &= \frac{1}{\lambda(1+\tilde{\delta})} \left[\frac{1}{N} \text{Tr}(\mathbf{T}) - \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \frac{\rho}{\beta} \frac{N}{K} (1+\rho+\delta\beta) \right] \\ &= \frac{1}{\lambda(1+\tilde{\delta})\beta} \left[\delta\beta \left(1 - \frac{\rho N}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right) - \frac{N}{K} \rho(1+\rho) \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right] \\ &= \frac{1}{\lambda(1+\tilde{\delta})\beta} \left[\left((1+\rho)\tilde{\delta} + \frac{N-K}{N\lambda} \beta \right) \left(1 - \frac{\rho N}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right) \right. \\ &\quad \left. - \rho(1+\rho) \frac{N}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right] \quad (83) \end{aligned}$$

$$\begin{aligned} &= \frac{1}{\lambda\beta} \left[\left((1+\rho) \frac{\tilde{\delta}}{1+\tilde{\delta}} + \frac{N-K}{N\lambda} \frac{\beta}{1+\tilde{\delta}} \right) \left(1 - \frac{\rho N}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^2} \right) \right. \\ &\quad \left. - \rho(1+\rho) \frac{N}{K} \frac{\tilde{\delta}^2}{(1+\tilde{\delta})^3} \right]. \quad (84) \end{aligned}$$

Plugging (78), (79) and (84) into Δ in Table I yields (69). With these expressions at hand, we are ready to simplify $\bar{\psi}$ and $\bar{s}_k = \lambda^2 ([\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{kk} - p_k \tilde{t}_k^2) + \tilde{s}'_k$. Since $\Theta = \mathbf{I}_N$, $\bar{\psi}$ writes as:

$$\begin{aligned} \bar{\psi} &= \frac{\vartheta}{\Delta} \frac{\lambda^2}{K} \text{Tr}(\mathbf{P}\tilde{\mathbf{T}}\tilde{\mathbf{D}}\tilde{\mathbf{T}}) + \frac{1-F}{\Delta(1+\tilde{\delta})^2} \frac{1}{K} \text{Tr}(\mathbf{P}\tilde{\mathbf{T}}\mathbf{A}^H \mathbf{A}\tilde{\mathbf{T}}) \\ &= \frac{\vartheta}{\Delta} \frac{\lambda^2}{K} \text{Tr}(\mathbf{P}) \frac{N}{K} \left(\frac{1+\rho}{\beta} \right) \frac{1}{N} \text{Tr}(\tilde{\mathbf{D}}^2 \tilde{\mathbf{T}}^2) \\ &\quad + \frac{(1-F)F}{\Delta} \frac{1+\rho}{\beta} \frac{N}{K} \frac{1}{K} \text{Tr}(\mathbf{P}) \quad (85) \end{aligned}$$

$$= \frac{1}{K} \text{Tr}(\mathbf{P}) \frac{N}{K} \frac{1+\rho}{\beta} \left(-1 + \frac{1-F}{\Delta} \right). \quad (86)$$

Plugging (78) into the above equation yields (72). We are now left with simplifying the expression of the interference term given in Corollary 5. Notice that $\tilde{\gamma}_l$ are all equal to $\tilde{\gamma} = \frac{N}{K} F \frac{1+\rho}{\beta}$. Hence,

$$\begin{aligned} &\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l + \frac{\vartheta}{\Delta} \frac{1}{N} \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{ll} \\ &= \frac{1-F}{\Delta} F \frac{N}{K} \frac{1+\rho}{\beta} \frac{1}{N} \text{Tr}(\mathbf{P}) + \frac{\lambda^2 \vartheta \tilde{\delta}}{\Delta} \frac{N}{K} \frac{1+\rho}{\beta} \frac{1}{N} \text{Tr}(\mathbf{P}) \\ &= \frac{N}{K} \frac{1+\rho}{\beta} \frac{1}{N} \text{Tr}(\mathbf{P}) \left(-1 + \frac{1-F}{\Delta} \right) \quad (87) \end{aligned}$$

while $\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{ll} + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l$ simplifies to:

$$\begin{aligned} &\frac{1-F}{\Delta} \frac{1}{N} \sum_{l=1}^K \lambda^2 \tilde{d}_l [\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{ll} + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \frac{1}{N} \sum_{l=1}^K p_l \tilde{\gamma}_l \\ &= \lambda^2 \frac{1}{N} \text{Tr}(\mathbf{P}) \frac{1+\rho}{\beta} \frac{N}{K} \tilde{\vartheta} \quad (88) \end{aligned}$$

Plugging (87) and (88) into the interference term $\bar{s}_k = \lambda^2([\mathbf{TP}\mathbf{T}]_{kk} - p_k \tilde{t}_k^2) + \bar{s}_k'$ given in Corollary 5 yields

$$\begin{aligned} \bar{s}_k &= \left(\frac{N}{K} \frac{1+\rho}{\beta} \right)^2 \lambda^2 \tilde{\vartheta} \frac{1}{N} \text{Tr}(\mathbf{P}) \left(-1 + \frac{1-F}{\Delta} \right) \\ &\quad + \frac{\lambda^2}{\Delta} F \frac{1}{N} \text{Tr}(\mathbf{P}) \left(\frac{N}{K} \frac{1+\rho}{\beta} \right)^2 \tilde{\vartheta} \end{aligned} \quad (89)$$

$$\begin{aligned} &= \lambda^2 \left(\frac{1+\rho}{\beta} \frac{N}{K} \right)^2 \frac{1}{N} \text{Tr}(\mathbf{P}) \tilde{\vartheta} \left(-1 + \frac{1}{\Delta} \right) \\ &= \lambda^2 \tilde{\delta}^2 \left(\frac{1+\rho}{\beta} \right)^2 \left(\frac{N}{K} \right)^3 \frac{1}{N} \text{Tr}(\mathbf{P}) \left(\frac{1}{\Delta} - 1 \right). \end{aligned} \quad (90)$$

This completes the proof. $\blacksquare$

Corollary 7 can be used to investigate the behavior of the signal power and interference for large values of the Rician factor ρ . Indeed, when $\rho \gg 1$ it is easy to see that $\tilde{\delta} = O(1/\rho)$. This is because $\tilde{\delta}$ is a deterministic equivalent of $\frac{1}{N} \text{Tr}(\mathbf{D}\mathbf{Q})$, which can be bounded above and below by constants proportional to $1/\rho$. With this observation at hand, from (67) we have that

$$\tilde{\delta} = \frac{K}{N} \frac{\beta}{(1+\rho)(\lambda+\beta)} + O(1/\rho^2) \quad (91)$$

and

$$\vartheta = \frac{K}{N(\lambda+\beta)^2} + \frac{N-K}{N\lambda^2} + (1/\rho). \quad (92)$$

By using the above identities, we have that Δ satisfies the following equation:

$$\Delta = 1 - \frac{2K}{N} \frac{\beta^2}{\rho(\lambda+\beta)^2} + O(1/\rho^2). \quad (93)$$

By plugging these results into (71) and (72), we obtain:

$$\bar{s}_k = \frac{2\lambda^2\beta^2}{\rho(\lambda+\beta)^4} \frac{1}{N} \text{Tr}(\mathbf{P}) + O(1/\rho^2) \quad (94)$$

and

$$\bar{\psi} = \frac{\beta}{(\lambda+\beta)^2} \frac{1}{K} \text{Tr}(\mathbf{P}) + O(1/\rho). \quad (95)$$

Moreover, the deterministic equivalent of the signal power can be also approximated by:

$$p_k \left(1 - \lambda \tilde{\delta} \frac{N}{K} \frac{1+\tilde{\delta}}{\beta} \right)^2 = p_k \left(1 - \frac{\lambda}{(\lambda+\beta)} \right)^2 + O(1/\rho). \quad (96)$$

All of this shows that the SINR increases as the Rician factor ρ grows. In addition to this, from Corollary 7 it follows that the asymptotic sum rate for RZF takes the form:

$$\bar{r}_E = \sum_{k=1}^K \log(1 + p_k \mu) \quad (97)$$

where

$$\mu = \frac{\bar{\gamma}_k}{p_k} = \frac{\left(1 - \lambda \tilde{\delta} \frac{N}{K} \left(\frac{1+\rho}{\beta} \right) \right)^2}{\bar{s}_k + \bar{\psi} \frac{\sigma^2}{N P_T}} \quad (98)$$

does not depend on k . Hence, the power allocation policy that maximize the sum rate in (97) subject to $\frac{1}{K} \text{Tr}(\mathbf{P}) = P$ with $p_k \geq 0$ is the uniform power allocation $p_k^* = \frac{1}{K} \text{Tr}(\mathbf{P})$ for all $k \in \{1, \dots, K\}$.

Fig. 1. Average rate per UE versus the number of antennas N when $K = 20$ and the Rician factor $\rho = 1$.

IV. NUMERICAL RESULTS

MC simulations are now used to validate the above asymptotic analysis for a network with finite dimensions.² We consider a cell of radius $R = 250$ m. We use the standard correlation model $[\Theta]_{i,j} = \eta^{|i-j|}$ and assume that the large scale coefficients β_k are obtained as [23], [30]

$$\beta_k = 2L_{\bar{x}} \left(1 + \frac{x_k^\kappa}{\bar{x}^\kappa} \right)^{-1}. \quad (99)$$

The parameter $\kappa > 2$ stands for the pathloss exponent, x_k denotes the distance of UE k from the BS, $\bar{x} > 0$ is a cut-off parameter where $L_{\bar{x}}$ is a constant that regulates the attenuation at distance $\bar{x}$. We assume $\kappa = 3.5$, $L_{\bar{x}} = -86.5$ dB and $\bar{x} = 25$ m. The results are obtained for 5000 channel realizations assuming that the UEs are randomly distributed in the circular region between $\bar{x}$ m and $R = 250$ m. We assume that the BS is outfitted with a uniform linear array, such that the n th entry of $\tilde{\mathbf{z}}_k$ is given by

$$[\tilde{\mathbf{z}}_k]_n = \exp(-j(n-1)\pi \sin \theta_k) \quad (100)$$

where θ_k is the angle of arrival associated with UE k and chosen such that $\sin \theta_k$ is uniformly distributed between $[-\sigma_A, \sigma_A]$ with σ_A being a constant controlling the angular spread of the LoS components at the BS. The transmit power P_T is fixed to 10 Watt and the regularization parameter λ is computed as $\lambda = \sigma^2 \mathbb{E}[\beta_k^{-1}] / P_T$, where the expectation is taken over the distribution of the UEs' positions.

Fig. 1 illustrates the average rate per UE when N grows large and K is kept fixed to 20. The correlation factor is set to $\eta = 0.5$ and σ_A takes the following values $\{0.4, 0.1, 0.05\}$ while the Rician factor is $\rho = 1$. The red curves are obtained using MC simulations whereas the black ones are obtained using the closed-form approximation of Theorem 2. As seen, the approximation matches perfectly with the MC

²The code is available online at <https://github.com/lucasanguinetti/> for testing different network configurations.

Fig. 2. Average rate per UE for low angular spreads when $N = 250$ and $K = 50$

simulations for any N . Therefore, we may conclude that the large system analysis is accurate even for networks of finite size. As seen, the average rate per UE improves as the angular spread increases (e.g., large values of σ_A). This is because the spatial separation or diversity of the LoS components of the different UEs increases as σ_A grows. A relatively good performance is achieved even for quite small values of σ_A . This means that a tiny spatial separation of the LoS vectors is not substantially detrimental for interference mitigation when $\rho = 1$ (which corresponds to the case in which the non-LoS and LoS components have the same strength).

The impact of the Rician coefficient ρ is investigated in Figs. 2 and 3 for $N = 250$ and $K = 50$ with different values of σ_A . As before, the approximation matches perfectly with the MC simulations for any ρ . Fig. 2 shows that, if σ_A is relatively small, the average rate reduces with ρ since the LoS vectors tend to be closely aligned in space, the average rate decreases as ρ grows. This is a consequence of the high inter-user interference. However, as σ_A increases Fig. 3 shows that an increase in the Rician coefficient has a positive effect on the rate performance. These results are in line with those reported in [29], wherein it is shown that large-scale MIMO systems benefit from LoS contributions when these are relatively different among the UEs.

V. CONCLUSIONS

This work analyzed the ergodic sum rate in the downlink of a single-cell large scale multi-user MIMO system operating over correlated Rician fading channels. A regularized zero-forcing precoding is employed under the assumption of perfect channel state information. Stating and proving new results from large-scale random matrix theory allowed us to provide accurate approximations of the SINRs of different UEs, from which the average rate expressions were obtained. Such approximations were shown to depend only on the system parameters (number of antennas and UEs) as well as

Fig. 3. Average rate per UE for high angular spreads when $N = 250$ and $K = 50$

on the long-term channel statistics; that is, the Rician factor and the spatial correlation matrix of UEs. Interesting insights were obtained and analytically characterized through a few illustrative examples. A set of Monte Carlo simulations were presented in order to illustrate the accuracy of the provided approximations and to show how they can lead to important insights into how the different parameters affect the network performance. To allow further investigation, the code used for Monte Carlo simulations was provided.

APPENDIX A PRELIMINARIES AND USEFUL RESULTS

We start defining $\tilde{\mathbf{Q}} = (\Sigma^H \Sigma + \lambda \mathbf{I}_N)^{-1}$ and $\mathbf{Q} = (\Sigma \Sigma^H + \lambda \mathbf{I}_N)^{-1}$. Matrix $\mathbf{T}$ and $\tilde{\mathbf{T}}$ are approximations of the resolvent matrices $\mathbf{Q}$ and $\tilde{\mathbf{Q}}$ in that:

$$\frac{1}{N} \text{Tr}(\mathbf{B}\mathbf{Q}) - \frac{1}{N} \text{Tr}(\mathbf{B}\mathbf{T}) \xrightarrow{\text{a.s.}} 0 \quad (101)$$

and

$$\frac{1}{N} \text{Tr}(\tilde{\mathbf{B}}\tilde{\mathbf{Q}}) - \frac{1}{N} \text{Tr}(\tilde{\mathbf{B}}\tilde{\mathbf{T}}) \xrightarrow{\text{a.s.}} 0 \quad (102)$$

for any sequence of matrices $\mathbf{B}$ and $\tilde{\mathbf{B}}$ of bounded spectral norm. Moreover, we also have

$$\mathbb{E} |\mathbf{u}^H \mathbf{Q} \mathbf{u} - \mathbf{u}^H \mathbf{T} \mathbf{u}|^p = \mathcal{O}(N^{-p/2}) \quad (103)$$

$$\mathbb{E} |\mathbf{u}^H \tilde{\mathbf{Q}} \mathbf{u} - \mathbf{u}^H \tilde{\mathbf{T}} \mathbf{u}|^p = \mathcal{O}(N^{-p/2}) \quad (104)$$

for any integer p and any sequence of vectors $\mathbf{u} \in \mathbb{C}^N$ with uniformly bounded norm. Let $\mathbf{Q}_k = (\Sigma_{[k]} \Sigma_{[k]}^H + \lambda \mathbf{I}_N)^{-1}$ where $\Sigma_{[k]}$ is obtained after removing column k from Σ .

Denote by $\tilde{q}_{kk}$ the k -th diagonal element of $\tilde{\mathbf{Q}}$. Then, the following relations hold true:

$$\tilde{q}_{kk} = \frac{1}{\lambda(1 + \boldsymbol{\eta}_k^H \mathbf{Q} \boldsymbol{\eta}_k)} \quad (105)$$

$$\mathbf{Q} = \mathbf{Q}_k - \lambda \tilde{q}_{kk} \mathbf{Q}_k \boldsymbol{\eta}_k \boldsymbol{\eta}_k^H \mathbf{Q}_k \quad (106)$$

$$\mathbf{Q} \boldsymbol{\eta}_k = \frac{\mathbf{Q}_k \boldsymbol{\eta}_k}{1 + \boldsymbol{\eta}_k^H \mathbf{Q}_k \boldsymbol{\eta}_k}. \quad (107)$$

Let δ and $\tilde{\delta}$ be the solutions to the following set of equations:

$$\delta = \frac{1}{N} \text{Tr}(\mathbf{D} \mathbf{T}) \quad (108)$$

$$\tilde{\delta} = \frac{1}{N} \text{Tr}(\tilde{\mathbf{D}} \tilde{\mathbf{T}}) \quad (109)$$

with

$$\mathbf{T} = \left(\lambda (\mathbf{I}_N + \tilde{\delta} \mathbf{D}) + \mathbf{A}_{[k]} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} \mathbf{A}^H \right)^{-1} \quad (110)$$

$$\tilde{\mathbf{T}} = \left(\lambda (\mathbf{I}_K + \delta \tilde{\mathbf{D}}) + \mathbf{A}^H (\mathbf{I}_N + \tilde{\delta} \mathbf{D})^{-1} \mathbf{A} \right)^{-1}. \quad (111)$$

The matrices $\mathbf{T}$ and $\tilde{\mathbf{T}}$ are respectively approximations of the resolvent matrices $\mathbf{Q}$ and $\tilde{\mathbf{Q}} = (\boldsymbol{\Sigma}^H \boldsymbol{\Sigma} - z \mathbf{I}_K)^{-1}$ such that

$$\frac{1}{N} \text{Tr}(\mathbf{B} \mathbf{Q}) - \frac{1}{N} \text{Tr}(\mathbf{B} \mathbf{T}) \xrightarrow{\text{a.s.}} 0 \quad (112)$$

$$\frac{1}{N} \text{Tr}(\tilde{\mathbf{B}} \tilde{\mathbf{Q}}) - \frac{1}{N} \text{Tr}(\tilde{\mathbf{B}} \tilde{\mathbf{T}}) \xrightarrow{\text{a.s.}} 0 \quad (113)$$

for any sequence of matrices $\mathbf{B} \in \mathbb{C}^{N \times N}$ and $\tilde{\mathbf{B}} \in \mathbb{C}^{K \times K}$ and

$$\mathbb{E} |\mathbf{u}^H \mathbf{Q} \mathbf{u} - \mathbf{u}^H \mathbf{T} \mathbf{u}|^p = \mathcal{O}(N^{-p/2}) \quad (114)$$

$$\mathbb{E} |\mathbf{u}^H \tilde{\mathbf{Q}} \mathbf{u} - \mathbf{u}^H \tilde{\mathbf{T}} \mathbf{u}|^p = \mathcal{O}(N^{-p/2}) \quad (115)$$

for any integer p and any sequence of vectors $\mathbf{u} \in \mathbb{C}^N$ with uniformly bounded norm.

Let us also introduce the following results and technical identities that will be extensively used in the remainder. Define the $N \times N$ matrix $\mathcal{T}_k$ for $k = 1, \dots, K$ as:

$$\mathcal{T}_k = \left(\lambda (\mathbf{I}_N + \tilde{\delta} \mathbf{D}) + \mathbf{A}_{[k]} (\mathbf{I}_{K-1} + \delta \tilde{\mathbf{D}}_{[k]})^{-1} \mathbf{A}_{[k]} \right)^{-1}$$

where $\mathbf{A}_{[k]}$ is $\mathbf{A}$ where column j has been removed while $\tilde{\mathbf{D}}_{[k]}$ is $\tilde{\mathbf{D}}$ where row and column k have been removed. We shall recall the following results that have been proved in [13] and [14].

- 1) Let $\mathbf{u}_N$ and $\mathbf{v}_N$ be two sequences of deterministic complex $N \times 1$ vectors with bounded Euclidean norm. For any integer p , There exists a constant K_p such that:

$$\mathbb{E} |\mathbf{u}_N^H \mathbf{Q}_\ell \mathbf{v}_N - \mathbf{u}_N^H \mathcal{T}_\ell \mathbf{v}_N|^p \leq \frac{K_p}{n^{p/2}}, \quad \ell = 1, \dots, K. \quad (116)$$

- 2) Let $\mathbf{b}$ be a $N \times 1$ vector. The following identity holds true:

$$\lambda \tilde{t}_{\ell\ell} \mathbf{a}_\ell^H \mathcal{T}_\ell \mathbf{b} = \frac{\mathbf{a}_\ell^H \mathbf{T} \mathbf{b}}{(1 + \tilde{d}_\ell \delta)} \quad \ell = 1, \dots, K. \quad (117)$$

- 3) For $\ell = 1, \dots, K$,

$$\tilde{t}_{\ell\ell} = \frac{1}{\lambda(1 + \mathbf{a}_\ell^H \mathcal{T}_\ell \mathbf{a}_\ell + \tilde{d}_\ell \delta)} \quad (118)$$

- 4) For any $\ell = 1, \dots, K$ and integer p , there exists a constant K_p such that:

$$\mathbb{E} |\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}|^p \leq \frac{K_p}{n^{\frac{p}{2}}}. \quad (119)$$

APPENDIX B

DETERMINISTIC EQUIVALENT FOR $\theta(\mathbf{v}, \mathbf{C})$ AND $\chi(\mathbf{C})$

A. Deterministic equivalent for $\theta(\mathbf{v}, \mathbf{C})$

We begin by observing that

$$\mathbf{Q} - \mathbf{T} \stackrel{(a)}{=} \mathbf{T} (\mathbf{T}^{-1} - \mathbf{Q}^{-1}) \mathbf{Q} \quad (120)$$

$$\stackrel{(b)}{=} \mathbf{T} \left(\lambda \tilde{\delta} \mathbf{D} + \mathbf{A} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} \mathbf{A}^H - \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H \right) \mathbf{Q} \quad (121)$$

where (a) follows from applying the resolvent identity³ and (b) is obtained by using (16) and $\mathbf{Q}^{-1} = \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H - \lambda \mathbf{I}_N$. Plugging the above expression into (23) leads to $\theta(\mathbf{v}, \mathbf{C}) = Z_1 + Z_2 + Z_3 - Z_4$ with

$$Z_1 = \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (122)$$

$$Z_2 = \lambda \tilde{\delta} \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (123)$$

$$Z_3 = \mathbb{E} \left[\mathbf{v}^H \mathbf{T} \mathbf{A} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} \mathbf{A}^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v} \right] \quad (124)$$

$$Z_4 = \mathbb{E} [\mathbf{v}^H \mathbf{T} \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v}]. \quad (125)$$

Notice that Z_2 will be compensated by some terms in Z_4 . This can be taken as a rule of thumb whenever the resolvent identity is used for computing deterministic equivalents (see [13]). Therefore, we restrict ourselves to the development of Z_1, Z_3 and Z_4 .

Let's start with Z_1 . From (103), it follows that:

$$Z_1 = \mathbf{v}^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{v} + \mathcal{O}(N^{-\frac{1}{2}}). \quad (126)$$

By using (106), we may write $Z_3 = Z_{3,1} + Z_{3,2}$ with

$$Z_{3,1} = \sum_{\ell=1}^K \mathbb{E} \left[\frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H}{1 + \delta \tilde{d}_\ell} \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v} \right] \quad (127)$$

$$Z_{3,2} = - \sum_{\ell=1}^K \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbb{E} [\lambda \tilde{q}_{\ell\ell} \mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}]}{1 + \delta \tilde{d}_\ell} \quad (128)$$

where $\{\tilde{q}_{\ell\ell}\}$ are the diagonal elements of $\tilde{\mathbf{Q}}$. We can prove that at the cost of an error $\mathcal{O}(N^{-\frac{1}{2}})$, we can replace in $Z_{3,2}$, $\tilde{q}_{\ell\ell}$ by $\tilde{t}_{\ell\ell}$ and $\mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell$ by $\mathbf{a}_\ell^H \mathcal{T}_\ell \mathbf{a}_\ell$ by using (116) and (119). Since the treatment of these terms is alike, we provide only the details concerning the replacement of $\tilde{q}_{\ell\ell}$ by $\tilde{t}_{\ell\ell}$. Let ϵ be given by:

$$\epsilon = - \sum_{\ell=1}^K \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbb{E} [\lambda (\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}) \mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}]}{1 + \delta \tilde{d}_\ell} \quad (129)$$

³ $\mathbf{A} - \mathbf{B} = \mathbf{B}(\mathbf{B}^{-1} - \mathbf{A}^{-1})\mathbf{A}$ [31].

Using Cauchy-Schwartz inequality:

$$|\epsilon| \leq \sqrt{\sum_{\ell=1}^K |\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell|^2 \mathbb{E} |\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}|^2 (1 + \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell)^2 (\mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell)^2} \\ \times \sqrt{\sum_{\ell=1}^K \mathbb{E} |\boldsymbol{\eta}_\ell^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v}|^2}. \quad (130)$$

From (119), $\mathbb{E} |\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}|^2 (1 + \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell)^2 (\mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell)^2 = O(N^{-\frac{1}{2}})$ and hence, $\epsilon = O(N^{-\frac{1}{2}})$. Hence, we obtain that $Z_{3,2} = U_1 + U_2 + O(N^{-\frac{1}{2}})$ with

$$U_1 = - \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \frac{\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{1 + \delta \tilde{d}_\ell} \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (131)$$

$$U_2 = - \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \frac{\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{1 + \delta \tilde{d}_\ell} \mathbb{E} [\mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}]. \quad (132)$$

By using (106) and replacing $\tilde{q}_{\ell\ell}$ with $\tilde{t}_{\ell\ell}$, U_2 can be further developed as:

$$U_2 = \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \frac{\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{1 + \delta \tilde{d}_\ell} \mathbb{E} [\mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{v}] \\ + O(N^{-1/2}). \quad (133)$$

By writing $\boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H = \mathbf{a}_\ell \mathbf{a}_\ell^H + \mathbf{a}_\ell \mathbf{y}_\ell^H + \mathbf{y}_\ell \mathbf{y}_\ell^H + \mathbf{y}_\ell \mathbf{a}_\ell^H$, it turns out that only $\mathbf{a}_\ell \mathbf{y}_\ell^H$ produces non-vanishing terms. Therefore, computing the expectation over $\mathbf{y}_\ell$ and using rank-one perturbation arguments [26, Lemma 7] we have:

$$U_2 = \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \frac{\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{1 + \delta \tilde{d}_\ell} \tilde{d}_\ell \mathbb{E} \left[\frac{1}{N} \text{Tr} (\mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q}) \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{v} \right] \\ + O(N^{-1/2}). \quad (134)$$

By using Lemma 5.2 in [13], we finally get:

$$U_2 = \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \frac{\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{(1 + \delta \tilde{d}_\ell)^2} \tilde{d}_\ell \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \mathbf{a}_\ell^H \mathbf{T} \mathbf{v} \\ + O(N^{-1/2}). \quad (135)$$

By collecting the above results and using the relation $\lambda \tilde{t}_{\ell\ell} = \frac{1 - \lambda \tilde{t}_{\ell\ell} \mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{1 + \delta \tilde{d}_\ell}$, we obtain:

$$Z_3 = \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] \\ + \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \tilde{d}_\ell \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \frac{\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell}{(1 + \delta \tilde{d}_\ell)^2} \mathbf{a}_\ell^H \mathbf{T} \mathbf{v} \\ + O(N^{-\frac{1}{2}}). \quad (136)$$

The first term in the above expression will be compensated by some terms in Z_4 and as such will not be worked out further. The second term contains $\chi(\mathbf{C})$ given by (24) unveiling the

interplay between $\theta(\mathbf{v}, \mathbf{C})$ and $\chi(\mathbf{C})$. Let's now move to the computation of Z_4 . By using $\mathbf{Q} \boldsymbol{\eta}_\ell = \lambda \tilde{q}_{\ell\ell} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell$, we obtain:

$$Z_4 = \sum_{\ell=1}^K \mathbf{v}^H \mathbf{T} \mathbb{E} [\lambda \tilde{q}_{\ell\ell} \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (137)$$

$$= \sum_{\ell=1}^K \mathbf{v}^H \mathbf{T} \mathbb{E} [\lambda \tilde{t}_{\ell\ell} \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] + O(N^{-\frac{1}{2}}) \quad (138)$$

$$= Z_{41} + Z_{42} + Z_{43} + Z_{44} + O(N^{-\frac{1}{2}}) \quad (139)$$

with

$$Z_{41} = \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbb{E} [\mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (140)$$

$$Z_{42} = \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbb{E} [\mathbf{y}_\ell \mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (141)$$

$$Z_{43} = \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbb{E} [\mathbf{y}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}] \quad (142)$$

$$Z_{44} = \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbb{E} [\mathbf{a}_\ell \mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q} \mathbf{v}]. \quad (143)$$

Since Z_{41} will be compensated by the first term in Z_3 , only the other terms will be considered. Let's start with Z_{42} . Using as usual the key decomposition in (106) along with the same techniques allowing the replacement of $\tilde{q}_{\ell\ell}$ by $\tilde{t}_{\ell\ell}$, we obtain:

$$Z_{42} = \sum_{\ell=1, \ell \neq k}^K \lambda \tilde{t}_{\ell\ell} \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{y}_\ell \mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{v}] \\ - \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell}^k)^2 \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{y}_\ell \mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{v}] + O(N^{-\frac{1}{2}}) \quad (144) \\ = \frac{1}{N} \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \tilde{d}_\ell \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{v}] \\ - \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{y}_\ell \mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{y}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{v}] \\ - \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{y}_\ell \mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{v}] + O(N^{-\frac{1}{2}}). \quad (145)$$

The third term in the above right-hand side is of order $O(N^{-\frac{1}{2}})$. For the same reasons, we can substitute in the second term $\mathbf{y}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{y}_\ell$ by $\tilde{d}_\ell \frac{1}{N} \text{Tr} \mathbf{E} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q}$. Moreover, in the first term $\mathbf{Q}_\ell$ can be replaced by $\mathbf{Q}$, which is in passing can be proven by decomposing $\mathbf{Q}_\ell$ as $\mathbf{Q}_\ell = \mathbf{Q} - \mathbf{Q} + \mathbf{Q}$ and using (106) along with the arguments developed so far. We

thus obtain:

$$\begin{aligned}
Z_{42} &= \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{v}] \\
&- \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{Q}_\ell \mathbf{v}] \frac{1}{N} \text{Tr} \mathbb{E} [\mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q}] \\
&+ \mathcal{O}(N^{-\frac{1}{2}}) \\
&= \lambda \tilde{\delta} \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v}] \\
&- \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \\
&+ \mathcal{O}(N^{-\frac{1}{2}}). \tag{146}
\end{aligned}$$

We look now to Z_{43} and Z_{44} . Using the same technicalities, we can prove that:

$$\begin{aligned}
Z_{43} &= -\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] \\
&+ \mathcal{O}(N^{-\frac{1}{2}}) \tag{148}
\end{aligned}$$

and

$$\begin{aligned}
Z_{44} &= -\mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{v}}{1 + \tilde{d}_\ell \delta} + \mathcal{O}(N^{-\frac{1}{2}}). \tag{149}
\end{aligned}$$

Gathering all these results together, we end up with the following expression for Z_4 :

$$\begin{aligned}
Z_4 &= \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{v}] + \lambda \tilde{\delta} \mathbb{E} [\mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{v}] \\
&- \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \\
&- \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] \\
&- \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \sum_{\ell=1}^K \lambda \tilde{t}_{\ell\ell} \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{v}}{1 + \tilde{d}_\ell \delta} + \mathcal{O}(N^{-\frac{1}{2}}). \tag{150}
\end{aligned}$$

The first two terms in Z_4 will be cancelled with Z_2 and some terms in Z_3 . We finally obtain:

$$\begin{aligned}
\theta(\mathbf{v}, \mathbf{C}) &= \mathbf{v}^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{v} \\
&+ \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \left[\sum_{\ell=1}^K \tilde{d}_\ell \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{v}}{(1 + \tilde{d}_\ell \delta)^2} \right. \\
&+ \left. \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \right] \\
&+ \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] + \mathcal{O}(N^{-\frac{1}{2}}). \tag{151}
\end{aligned}$$

Equation (151) establishes a relation between $\theta(\mathbf{v}, \mathbf{C})$ and the unknown quantities $\mathbb{E} [\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q}]$ and $\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell]$. Quantity $\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell]$ can be related to $\theta(\mathbf{a}_\ell, \mathbf{C})$ as:

$$\begin{aligned}
\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{a}_\ell] &= \lambda^2 (\tilde{t}_{\ell\ell})^2 (1 + \tilde{d}_\ell \delta)^2 \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] \\
&+ \tilde{d}_\ell \left(\frac{\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell}{1 + \tilde{d}_\ell \delta} \right)^2 \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] + \mathcal{O}(N^{-\frac{1}{2}}). \tag{152}
\end{aligned}$$

This can be proven by substituting in $\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{a}_\ell]$, matrix $\mathbf{Q}$ by $\mathbf{Q}_\ell - \lambda \tilde{q}_\ell \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell$ as per (106), and controlling the vanishing terms. To determine $\theta(\mathbf{v}, \mathbf{C})$, it is easy to see that we need a second equation between $\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{C} \mathbf{Q} \mathbf{a}_\ell]$ and $\mathbb{E} [\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q}]$. This is the objective of the subsequent section.

B. Deterministic equivalent for χ_C

By using the resolvent identity and then handling each term separately (derivations are similar to before, and hence details are omitted), after some calculations we obtain

$$\begin{aligned}
\mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] &= \frac{1}{N} \text{Tr} \mathbf{D} \mathbf{T} \mathbf{C} \mathbf{T} \\
&+ \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{D} \mathbf{Q} \right] \left[\frac{1}{N} \sum_{\ell=1}^K \frac{\tilde{d}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{a}_\ell}{(1 + \delta \tilde{d}_\ell)^2} \right. \\
&+ \left. \frac{1}{N} \sum_{\ell=1}^K \lambda^2 \tilde{d}_\ell^2 (\tilde{t}_{\ell\ell})^2 \frac{1}{N} \text{Tr} \mathbf{D} \mathbf{T} \mathbf{C} \mathbf{T} \right] \\
&+ \frac{1}{N} \text{Tr} \mathbf{D} \mathbf{T} \mathbf{C} \mathbf{T} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_\ell] + \mathcal{O}(N^{-\frac{1}{2}}). \tag{153}
\end{aligned}$$

Now let $m \in \{1, K\}$. Then, from (151) we have

$$\begin{aligned}
\mathbb{E} [\mathbf{a}_m^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_m] &= \mathbf{a}_m^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{a}_m \\
&+ \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \left[\sum_{\ell=1}^K \frac{\tilde{d}_\ell \mathbf{a}_m^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_\ell \delta)^2} \right. \\
&+ \left. \mathbf{a}_m^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_m \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \right] \\
&+ \mathbf{a}_m^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_m \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] + \mathcal{O}(N^{-\frac{1}{2}}). \tag{154}
\end{aligned}$$

By multiplying both sides by $\frac{\tilde{d}_m}{(1 + \tilde{d}_m \delta)^2}$ and summing over m , we obtain:

$$\begin{aligned}
\frac{1}{N} \sum_{m=1}^K \frac{\tilde{d}_m \mathbb{E} [\mathbf{a}_m^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_m]}{(1 + \tilde{d}_m \delta)^2} &= \frac{1}{N} \sum_{m=1}^K \frac{\tilde{d}_m \mathbf{a}_m^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_m \delta)^2} \\
&+ \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \left[\frac{1}{N} \sum_{\ell=1}^K \sum_{m=1}^K \frac{\tilde{d}_\ell \tilde{d}_m \mathbf{a}_m^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_\ell \delta)^2 (1 + \tilde{d}_m \delta)^2} \right. \\
&+ \left. \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \frac{1}{N} \sum_{m=1}^K \frac{\mathbf{a}_m^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_m \tilde{d}_m}{(1 + \tilde{d}_m \delta)^2} \right] \\
&+ \frac{1}{N} \sum_{m=1}^K \frac{\tilde{d}_m \mathbf{a}_m^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_m \delta)^2} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] \\
&+ \mathcal{O}(N^{-\frac{1}{2}})
\end{aligned}$$

from which, by using (152), we obtain (156) on the top of next page. By defining the following quantities

$$\varphi(\mathbf{C}) = \frac{1}{N} \sum_{\ell=1}^K \tilde{d}_\ell \lambda^2 (\tilde{t}_{\ell\ell})^2 \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] \quad (157)$$

$$F(\mathbf{C}) = \frac{1}{N} \sum_{m=1}^K \frac{\tilde{d}_m \mathbf{a}_m^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_m \delta)^2} \quad (158)$$

$$G = \frac{1}{N} \sum_{m=1}^K \sum_{\ell=1}^K \tilde{d}_\ell \tilde{d}_m \frac{\mathbf{a}_m^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{a}_m}{(1 + \tilde{d}_\ell \delta)^2 (1 + \tilde{d}_m \delta)^2} - \frac{1}{N} \sum_{\ell=1}^K \tilde{d}_\ell^2 \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \quad (159)$$

$$M = \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \quad (160)$$

we can write (156) as:

$$(1 - F)\varphi(\mathbf{C}) = F(\mathbf{C}) + \chi(\mathbf{C}) (G + MF) + \mathcal{O}(N^{-\frac{1}{2}}). \quad (161)$$

Let $\vartheta(\mathbf{C}) = \frac{1}{N} \text{Tr} \mathbf{D} \mathbf{T} \mathbf{C} \mathbf{T}$. We also write (153) as:

$$\chi(\mathbf{C}) = \vartheta(\mathbf{C}) + \chi(\mathbf{D}) (F(\mathbf{C}) + M\vartheta(\mathbf{C})) + \vartheta(\mathbf{C})\varphi(\mathbf{D}) + \mathcal{O}(N^{-\frac{1}{2}}) \quad (162)$$

Let $\Delta = (1 - F)^2 - M\vartheta - \vartheta G$. From Lemma 5.3 in [13], Δ satisfies also $\Delta = (1 - F)^2 - \lambda^2 \vartheta \tilde{\vartheta}$ which merely results from the fact that $G + M = \lambda^2 \tilde{\vartheta}$. Setting $\mathbf{C}$ to $\mathbf{D}$ in (161) and (162) we thus obtain: $\chi(\mathbf{D}) = \frac{\vartheta}{\Delta} + \mathcal{O}(N^{-\frac{1}{2}})$ and $\varphi(\mathbf{D}) = -1 + \frac{1-F}{\Delta} - \frac{M\vartheta}{\Delta} + \mathcal{O}(N^{-\frac{1}{2}})$. We thus get:

$$\chi(\mathbf{C}) = \frac{\vartheta(\mathbf{C})(1 - F)}{\Delta} + \frac{\vartheta F(\mathbf{C})}{\Delta} + \mathcal{O}(N^{-\frac{1}{2}}). \quad (163)$$

Plugging the above expression into (161), we thus obtain after some calculations:

$$\varphi(\mathbf{C}) = \vartheta(\mathbf{C}) \left(\frac{M(F - 1)}{\Delta} + \frac{\lambda^2 \tilde{\vartheta}}{\Delta} \right) + F(\mathbf{C}) \left(\frac{1 - F}{\Delta} - \frac{M\vartheta}{\Delta} \right) + \mathcal{O}(N^{-\frac{1}{2}}) \quad (164)$$

and

$$\begin{aligned} \theta(\mathbf{v}, \mathbf{C}) &= \mathbf{v}^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{v} \\ &+ \sum_{\ell=1}^K \tilde{d}_\ell \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{v}}{(1 + \tilde{d}_\ell \delta)^2} \left(\frac{\vartheta(\mathbf{C})(1 - F)}{\Delta} + \frac{\vartheta F(\mathbf{C})}{\Delta} \right) \\ &+ \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} \left(\frac{F(\mathbf{C})(1 - F)}{\Delta} + \frac{\lambda^2 \tilde{\vartheta} \vartheta(\mathbf{C})}{\Delta} \right) + \mathcal{O}(N^{-\frac{1}{2}}). \end{aligned} \quad (165)$$

In particular, if $\mathbf{C} = \mathbf{D}$ we obtain:

$$\theta(\mathbf{v}, \mathbf{D}) = \frac{1 - F}{\Delta} \mathbf{v}^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{v} + \frac{\vartheta}{\Delta} \sum_{\ell=1}^K \tilde{d}_\ell \frac{\mathbf{v}^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{v}}{(1 + \tilde{d}_\ell \delta)^2}. \quad (166)$$

APPENDIX C PROOF OF THEOREM 2

Let $\boldsymbol{\eta}_k$ denote the k th column of $\boldsymbol{\Sigma}$. Then, the SINR at UE k can be rewritten as:

$$\gamma_k = \frac{p_k |\boldsymbol{\eta}_k^H \mathbf{Q} \boldsymbol{\eta}_k|^2}{\sum_{i=1, i \neq k}^K p_i |\boldsymbol{\eta}_k^H \mathbf{Q} \boldsymbol{\eta}_i|^2 + \frac{\sigma^2}{N P_T} \frac{1}{K} \text{Tr} \mathbf{P} \boldsymbol{\Sigma}^H \mathbf{Q}^2 \boldsymbol{\Sigma}} \quad (167)$$

from which it follows that γ_k can be expressed as functionals of the resolvent matrix $\mathbf{Q}$. By applying (106), we obtain

$$\mathbf{Q} \boldsymbol{\eta}_k = \frac{\mathbf{Q}_k \boldsymbol{\eta}_k}{1 + \boldsymbol{\eta}_k^H \mathbf{Q}_k \boldsymbol{\eta}_k} = \lambda \tilde{q}_{kk} \mathbf{Q}_k \boldsymbol{\eta}_k \quad (168)$$

where $\mathbf{Q}_k = (\boldsymbol{\Sigma}_{[k]} \boldsymbol{\Sigma}_{[k]}^H + \lambda \mathbf{I}_N)^{-1}$. Plugging (168) into (167) yields:

$$\gamma_k = \frac{p_k (1 - \lambda \tilde{q}_{kk})^2}{s_k + \frac{\sigma^2}{N P_T} \psi} \quad (169)$$

where we have defined

$$s_k = \lambda^2 \tilde{q}_{kk}^2 \boldsymbol{\eta}_k^H \mathbf{Q}_k \boldsymbol{\Sigma}_{[k]} \mathbf{P}_{[k]} \boldsymbol{\Sigma}_{[k]}^H \mathbf{Q}_k \boldsymbol{\eta}_k \quad (170)$$

$$\psi = \frac{1}{K} \text{Tr} (\mathbf{P} \boldsymbol{\Sigma}^H \mathbf{Q}^2 \boldsymbol{\Sigma}). \quad (171)$$

Therefore, computing an asymptotic approximation for γ_k requires to determine asymptotic approximations for $\tilde{q}_{kk}$, s_k and ψ . From (119), it easily follows that $\tilde{q}_{kk} - \tilde{t}_{kk} \xrightarrow{\text{a.s.}} 0$. The computation of the asymptotic approximations for s_k and ψ is more involved and is addressed in the following.

A.1) Deterministic equivalent for s_k

The computation of a deterministic equivalent for the interference term s_k is much more involved. In short, the approach taken in the remainder basically relies on showing that the interference term s_k is asymptotically given by the weighted sum of two terms, whose approximations depend on quantities in the same form of those of Theorem 1. Simplifications are then performed by combining both deterministic equivalents.

We begin by applying Lemma 1 in Appendix C to $\check{s}_k \triangleq \boldsymbol{\eta}_k^H \mathbf{Q}_k \boldsymbol{\Sigma}_{[k]} \mathbf{P}_{[k]} \boldsymbol{\Sigma}_{[k]}^H \mathbf{Q}_k \boldsymbol{\eta}_k$ and then use Lemma 2 to obtain $\max_k |\check{s}_k - \tilde{d}_k \check{s}_{k,1} - \check{s}_{k,2}| \xrightarrow{\text{a.s.}} 0$ with

$$\check{s}_{k,1} = \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q}_k \boldsymbol{\Sigma}_{[k]} \mathbf{P}_{[k]} \boldsymbol{\Sigma}_{[k]}^H \mathbf{Q}_k \right] \quad (172)$$

and

$$\check{s}_{k,2} = \mathbb{E} \left[\mathbf{a}_k^H \mathbf{Q}_k \boldsymbol{\Sigma}_{[k]} \mathbf{P}_{[k]} \boldsymbol{\Sigma}_{[k]}^H \mathbf{Q}_k \mathbf{a}_k \right]. \quad (173)$$

From the convergence result of $\tilde{q}_{kk}$ established above, we have:

$$\max_k \left| \tilde{s}_k - \tilde{d}_k \lambda^2 \tilde{t}_{kk}^2 \check{s}_{k,1} - \lambda^2 \tilde{t}_{kk}^2 \check{s}_{k,2} \right| \rightarrow 0. \quad (174)$$

Due to finite rank perturbation arguments, we can easily show that:

$$\check{s}_{k,1} = \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \boldsymbol{\Sigma}_{[k]} \mathbf{P}_{[k]} \boldsymbol{\Sigma}_{[k]}^H \mathbf{Q} \right] + \mathcal{O}(N^{-1})$$

$$\begin{aligned}
& \frac{1}{N} \sum_{\ell=1}^K \tilde{d}_\ell \lambda^2 (\tilde{t}_{\ell\ell})^2 \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] = \frac{1}{N} \sum_{m=1}^K \frac{\tilde{d}_m \mathbf{a}_m^H \mathbf{T} \mathbf{C} \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_m \delta)^2} + \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{C} \mathbf{Q} \right] \\
& \times \left[\frac{1}{N} \sum_{m=1}^K \sum_{\ell=1}^K \tilde{d}_\ell \tilde{d}_m \frac{\mathbf{a}_m^H \mathbf{T} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{a}_m}{(1 + \tilde{d}_\ell \delta)^2 (1 + \tilde{d}_m \delta)^2} - \frac{1}{N} \sum_{\ell=1}^K \tilde{d}_\ell^2 \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} + \frac{1}{N} \sum_{m=1}^K \frac{\tilde{d}_m \mathbf{a}_m^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_m \delta)^2} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell^2 \right] \\
& + \frac{1}{N} \sum_{m=1}^K \tilde{d}_m \frac{\mathbf{a}_m^H \mathbf{T} \mathbf{D} \mathbf{T} \mathbf{a}_m}{(1 + \tilde{d}_m \delta)^2} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 (\tilde{t}_{\ell\ell})^2 \tilde{d}_\ell \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{C} \mathbf{Q}_\ell \mathbf{a}_\ell] + \mathcal{O}(N^{-\frac{1}{2}}). \tag{156}
\end{aligned}$$

However, the replacement of $\mathbf{Q}_k$ by $\mathbf{Q}$ in $\check{s}_{k,2}$ is not allowed. To determine the error incurred by such a replacement, we shall study the following quantity:

$$\check{s}_{k,2} = \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q} \mathbf{a}_k]$$

Using the relation $\mathbf{Q} = \mathbf{Q}_k - \lambda \tilde{q}_{kk} \mathbf{Q}_k \boldsymbol{\eta}_k \boldsymbol{\eta}_k^H \mathbf{Q}_k$, we have:

$$\begin{aligned}
\mathbf{a}_k^H \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q} \mathbf{a}_k &= \mathbf{a}_k^H \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \mathbf{a}_k \\
&- \lambda \tilde{q}_{kk} \mathbf{a}_k^H \mathbf{Q}_k \boldsymbol{\eta}_k \boldsymbol{\eta}_k^H \mathbf{Q}_k \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \mathbf{a}_k \\
&- \lambda \tilde{q}_{kk} \mathbf{a}_k^H \mathbf{Q}_k \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \boldsymbol{\eta}_k \boldsymbol{\eta}_k^H \mathbf{Q}_k \mathbf{a}_k \\
&+ \lambda^2 \tilde{q}_{kk}^2 \mathbf{a}_k^H \mathbf{Q}_k \boldsymbol{\eta}_k \boldsymbol{\eta}_k^H \mathbf{Q}_k \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \boldsymbol{\eta}_k \boldsymbol{\eta}_k^H \mathbf{Q}_k \mathbf{a}_k
\end{aligned}$$

Using Lemma 1 in Appendix B along with the approximations in (116) and (119), we thus obtain:

$$\begin{aligned}
\check{s}_{k,2} &= (1 - \lambda \tilde{t}_{kk} \mathbf{a}_k^H \mathbf{T}_k \mathbf{a}_k)^2 \mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_k \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \mathbf{a}_k] \\
&+ \tilde{d}_k \lambda^2 \tilde{t}_{kk}^2 (\mathbf{a}_k^H \mathbf{T}_k \mathbf{a}_k)^2 \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q} \right] + \mathcal{O}(N^{-\frac{1}{2}})
\end{aligned}$$

Using (117) and (118), we thus obtain:

$$\begin{aligned}
\check{s}_{k,2} &= \lambda^2 \tilde{t}_{kk}^2 (1 + \tilde{d}_k \delta)^2 \mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_k \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \mathbf{a}_k] \\
&+ \frac{(\mathbf{a}_k^H \mathbf{T} \mathbf{a}_k)^2 \tilde{d}_k}{(1 + \tilde{d}_k \delta)^2} \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q} \right] + \mathcal{O}(N^{-\frac{1}{2}}) \tag{175}
\end{aligned}$$

which proves that:

$$\begin{aligned}
\mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_k \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q}_k \mathbf{a}_k] &= \frac{\mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q} \mathbf{a}_k]}{\lambda^2 \tilde{t}_{kk}^2 (1 + \tilde{d}_k \delta)^2} \\
&- \frac{(\mathbf{a}_k^H \mathbf{T} \mathbf{a}_k)^2 \tilde{d}_k}{(1 + \tilde{d}_k \delta)^4 \lambda^2 \tilde{t}_{kk}^2} \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \Sigma_{[k]} \mathbf{P}_{[k]} \Sigma_{[k]}^H \mathbf{Q} \right] + \mathcal{O}(N^{-\frac{1}{2}})
\end{aligned}$$

We thus obtain:

$$\max_k \left| \check{s}_k - \frac{\check{s}_{k,2}}{(1 + \tilde{d}_k \delta)^2} - \left(\tilde{d}_k \lambda^2 \tilde{t}_{kk}^2 - \frac{\tilde{d}_k (\mathbf{a}_k^H \mathbf{T} \mathbf{a}_k)^2}{(1 + \tilde{d}_k \delta)^4} \right) \check{s}_{k,1} \right| \xrightarrow{\text{a.s.}} 0. \tag{176}$$

C. Deterministic equivalent for $\check{s}_{k,1}$

To begin with, observe that:

$$\check{s}_{k,1} = \frac{1}{N} \sum_{\ell=1}^K \lambda^2 p_\ell \mathbb{E} [\tilde{q}_{\ell\ell}^2 \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell] \tag{177}$$

$$= \frac{1}{N} \sum_{\ell=1}^K \lambda^2 p_\ell \tilde{t}_{\ell\ell}^2 \mathbb{E} [\boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell] + \mathcal{O}(N^{-\frac{1}{2}}) \tag{178}$$

As seen the replacement of $\tilde{q}_{\ell\ell}$ by $\tilde{t}_{\ell\ell}$ allows to express $\check{s}_{k,1}$ as classical quadratic form - up to a vanishing term $\mathcal{O}(N^{-\frac{1}{2}})$. By taking the expectation with respect to $\boldsymbol{\eta}_\ell$, we obtain:

$$\mathbb{E} [\boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell] = \tilde{d}_\ell \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \right] + \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_\ell] \tag{179}$$

To proceed further, we rewrite the two terms above as function of $\mathbf{Q}$ (rather than $\mathbf{Q}_\ell$). By applying twice Lemma 3.1 [13], the first term is such that:

$$\left| \frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell - \frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{D} \mathbf{Q} \right| \leq \frac{2 \|\mathbf{D}\|^2}{N \lambda^2}$$

The second term in (179) is a quadratic form (not a normalized trace) and thus cannot be treated in the same way. We need to develop $\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_\ell]$. By using (106), we obtain:

$$\begin{aligned}
\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_\ell] &= \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_\ell] \\
&+ \lambda^2 \mathbb{E} [\tilde{q}_{\ell\ell}^2 \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell | \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_\ell]^2 \\
&- \lambda \mathbb{E} [\tilde{q}_{\ell\ell} \mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_\ell] - \lambda \mathbb{E} [\tilde{q}_{\ell\ell} \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_\ell] \tag{180}
\end{aligned}$$

By using (116) and (119) and taking the expectation with respect to $\boldsymbol{\eta}_\ell$, we obtain:

$$\begin{aligned}
\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_\ell] &= \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_\ell] (1 - \lambda \tilde{t}_{\ell\ell} \mathbf{a}_\ell^H \mathbf{T}_\ell \mathbf{a}_\ell)^2 \\
&+ \lambda^2 \tilde{t}_{\ell\ell}^2 (\mathbf{a}_\ell^H \mathbf{T}_\ell \mathbf{a}_\ell)^2 \tilde{d}_\ell \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \right] + \mathcal{O}(N^{-\frac{1}{2}}) \tag{181}
\end{aligned}$$

From the results of (118) and (117), the above expression can be equivalently rewritten as function of $\mathbf{T}$ as follows:

$$\begin{aligned}
\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_\ell] &= \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_\ell] \lambda^2 \tilde{t}_{\ell\ell}^2 (1 + \tilde{d}_\ell \delta)^2 \\
&+ \left(\frac{\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell}{(1 + \tilde{d}_\ell \delta)} \right)^2 \tilde{d}_\ell \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{D} \mathbf{Q} \right] + \mathcal{O}(N^{-\frac{1}{2}}) \tag{182}
\end{aligned}$$

Plugging the above results into (177) yields:

$$\begin{aligned}
\check{s}_{k,1} &= \frac{1}{N} \sum_{\ell=1}^K p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_\ell] \\
&+ \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{D} \mathbf{Q} \right] \left(\frac{1}{N} \sum_{\ell=1}^K p_\ell \tilde{d}_\ell \lambda^2 \tilde{t}_{\ell\ell}^2 \right. \\
&\left. - \frac{1}{N} \sum_{\ell=1}^K p_\ell \tilde{d}_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \right) + \mathcal{O}(N^{-\frac{1}{2}}) \tag{183}
\end{aligned}$$

which turns out to be only a function of $\mathbb{E} [\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q} \mathbf{D} \mathbf{Q}]$ and $\mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_\ell]$. Corollary 1 and Corollary 2 are now used to get deterministic equivalents for both terms. We thus obtain:

$$\begin{aligned}
\tilde{s}_{k,1} &= \frac{1}{N} \sum_{\ell=1}^K \frac{1-F}{\Delta} p_\ell \tilde{\gamma}_\ell \\
&+ \frac{\vartheta}{\Delta} \left(\frac{1}{N} \sum_{\ell=1}^K \lambda^2 p_\ell [\tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}}]_{\ell\ell} - \frac{1}{N} \sum_{\ell=1}^K \lambda^2 p_\ell \tilde{d}_\ell \tilde{t}_{\ell\ell}^2 \right. \\
&+ \left. \frac{1}{N} \sum_{\ell=1}^K \tilde{d}_\ell p_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \right) \\
&+ \frac{\vartheta}{\Delta} \left(\frac{1}{N} \sum_{\ell=1}^K \lambda^2 p_\ell \tilde{d}_\ell \tilde{t}_{\ell\ell}^2 - \frac{1}{N} \sum_{\ell=1}^K \tilde{d}_\ell p_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \right) + \mathcal{O}(N^{-\frac{1}{2}}) \\
&= \frac{1}{N} \sum_{\ell=1}^K \frac{1-F}{\Delta} p_\ell \tilde{\gamma}_\ell + \frac{\vartheta}{\Delta} \frac{1}{N} \sum_{\ell=1}^K \lambda^2 p_\ell [\tilde{\mathbf{T}} \tilde{\mathbf{D}} \tilde{\mathbf{T}}]_{\ell\ell} + \mathcal{O}(N^{-\frac{1}{2}}).
\end{aligned} \tag{184}$$

D. Deterministic equivalent for $\check{s}_{k,2}$

To begin with, we expand $\check{s}_{k,2}$ as:

$$\begin{aligned}
\check{s}_{k,2} &= \sum_{\ell \neq k} p_\ell \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q} \mathbf{a}_k] \\
&= \sum_{\ell \neq k} p_\ell \lambda^2 \mathbb{E} [\tilde{q}_{\ell\ell}^2 \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q} \mathbf{a}_k] \\
&= \sum_{\ell \neq k} p_\ell \lambda^2 \mathbb{E} [\tilde{t}_{\ell\ell}^2 \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q} \mathbf{a}_k] + \epsilon
\end{aligned}$$

where

$$\epsilon = \sum_{\ell \neq k} p_\ell \lambda^2 \mathbb{E} [(\tilde{q}_{\ell\ell}^2 - \tilde{t}_{\ell\ell}^2) \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q} \mathbf{a}_k].$$

Since $\max(\tilde{q}_{\ell\ell}, \tilde{t}_{\ell\ell}) \leq \lambda^{-1}$, we have:

$$|\epsilon| \leq 2\lambda \sum_{\ell \neq k} p_\ell \mathbb{E} [|\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}| \boldsymbol{\eta}_\ell^H \mathbf{Q} \mathbf{a}_k \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell] = \epsilon_1 + \epsilon_2$$

with

$$\begin{aligned}
\epsilon_1 &= 2\lambda \sum_{\ell \neq k} p_\ell \mathbb{E} [|\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}| \mathbf{y}_\ell^H \mathbf{Q} \mathbf{a}_k \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell] \\
\epsilon_2 &= 2\lambda \sum_{\ell \neq k} p_\ell \mathbb{E} [|\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}| \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell].
\end{aligned}$$

To control ϵ_1 , we make use of the Jensen and Cauchy-Schwartz inequality such that:

$$\begin{aligned}
|\epsilon_1| &\leq \sqrt{\sum_{\ell \neq k} 4\lambda^2 p_\ell^2 \mathbb{E} [|\mathbf{y}_\ell^H \mathbf{Q} \mathbf{a}_k|^2 |\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}|^2 (1 + \boldsymbol{\eta}_\ell^H \mathbf{Q} \boldsymbol{\eta}_\ell)^2]} \\
&\times \sqrt{\sum_{\ell \neq k} |\mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell|^2} = \mathcal{O}(N^{-\frac{1}{2}})
\end{aligned}$$

One can easily convince himself that the same arguments used for ϵ_1 allow to replace $\mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k$ with $\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_k$ in ϵ_2 with an inducing error of order $\mathcal{O}(N^{-\frac{1}{2}})$. This is because the

difference $\mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k - \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_k$ would behave like $\mathbf{y}_\ell^H \mathbf{Q} \mathbf{a}_k$. We thus obtain:

$$\begin{aligned}
|\epsilon_2| &= \left| 2\lambda \sum_{\ell \neq k} p_\ell \mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_k \mathbb{E} [|\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}| \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell (1 + \boldsymbol{\eta}_\ell^H \mathbf{Q} \boldsymbol{\eta}_\ell)] \right| \\
&+ \mathcal{O}(N^{-\frac{1}{2}}) \\
&= \left| 2 \sum_{\ell \neq k} p_\ell \frac{\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_k}{\tilde{t}_{\ell\ell} (1 + \tilde{\delta} d_\ell)} \mathbb{E} [|\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}| \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\eta}_\ell (1 + \boldsymbol{\eta}_\ell^H \mathbf{Q} \boldsymbol{\eta}_\ell)] \right| \\
&+ \mathcal{O}(N^{-\frac{1}{2}}) \\
&= \left| 2 \mathbf{a}_k^H \mathbf{Q} \boldsymbol{\Sigma} \text{diag} \left\{ \frac{p_\ell (1 + \boldsymbol{\eta}_\ell^H \mathbf{Q} \boldsymbol{\eta}_\ell) |\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}|}{\tilde{t}_{\ell\ell} (1 + \tilde{\delta} d_\ell)} \boldsymbol{\delta}_{\ell \neq k} \right\}_{\ell=1}^K \mathbf{A}^H \mathbf{T} \mathbf{a}_k \right| \\
&+ \mathcal{O}(N^{-\frac{1}{2}}) \\
&\leq 2 \|\mathbf{a}_k\|_2 \|\mathbf{Q} \boldsymbol{\Sigma}\| \\
&\times \sqrt{\sum_{\ell \neq k} p_\ell^2 \mathbb{E} \left[\frac{(1 + \boldsymbol{\eta}_\ell^H \mathbf{Q} \boldsymbol{\eta}_\ell)^2 |\tilde{q}_{\ell\ell} - \tilde{t}_{\ell\ell}|^2}{\tilde{t}_{\ell\ell}^2 (1 + \tilde{\delta} d_\ell)^2} \right] |\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_k|^2} + \mathcal{O}(N^{-\frac{1}{2}}).
\end{aligned}$$

Noting that $\|\mathbf{Q} \boldsymbol{\Sigma}\|$ is bounded yields $\epsilon_2 = \mathcal{O}(N^{-\frac{1}{2}})$. Taking the expectation with respect to $\boldsymbol{\eta}_\ell$, we obtain:

$$\begin{aligned}
\check{s}_{k,2} &= \sum_{\ell \neq k} \frac{1}{N} \lambda^2 \tilde{t}_{\ell\ell}^2 p_\ell \tilde{d}_\ell \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_k] \\
&+ \sum_{\ell \neq k} \lambda^2 \tilde{t}_{\ell\ell}^2 p_\ell \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k] + \mathcal{O}(N^{-\frac{1}{2}}).
\end{aligned}$$

We can easily prove (details are omitted) that due to the normalization factor $\frac{1}{N}$, it is possible to replace up to an error $\mathcal{O}(N^{-1})$ $\mathbf{Q}_\ell$ by $\mathbf{Q}$, leading to:

$$\begin{aligned}
\sum_{\ell \neq k} \frac{1}{N} \lambda^2 \tilde{t}_{\ell\ell}^2 p_\ell \tilde{d}_\ell \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_k] &= \sum_{\ell \neq k} \frac{1}{N} \lambda^2 \tilde{t}_{\ell\ell}^2 p_\ell \tilde{d}_\ell \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_k] \\
&+ \mathcal{O}(N^{-1}).
\end{aligned}$$

This replacement is not allowed for the second term. To handle this term, we shall study $\mathbb{E} [\sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k]$. Using the relation $\mathbf{Q} = \mathbf{Q}_\ell - \lambda \tilde{q}_{\ell\ell} \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell$, we obtain:

$$\begin{aligned}
&\mathbb{E} \left[\sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k \right] \\
&= \sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k] \\
&- \sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbb{E} [\lambda \tilde{q}_{\ell\ell} \mathbf{a}_k^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k] \\
&- \sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbb{E} [\lambda \tilde{q}_{\ell\ell} \mathbf{a}_k^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k] \\
&+ \sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbb{E} [\lambda^2 \tilde{q}_{\ell\ell}^2 \mathbf{a}_k^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \boldsymbol{\eta}_\ell \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k].
\end{aligned}$$

Using the same arguments employed to handle ϵ , it is easy to see that $\tilde{q}_{\ell\ell}$ can be replaced by $\tilde{t}_{\ell\ell}$ and $\boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell \mathbf{a}_\ell$ by $\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell$, which leads to:

$$\begin{aligned} & \mathbb{E} \left[\sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k \right] \\ &= \sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} (1 - \lambda \tilde{t}_{\ell\ell} \mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell)^2 \mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k] \\ &+ \sum_{\ell \neq k} \lambda^2 \tilde{t}_{\ell\ell}^2 \tilde{d}_\ell p_\ell (1 + \tilde{d}_\ell \delta)^{-2} (\mathbf{a}_\ell^H \boldsymbol{\tau}_\ell \mathbf{a}_\ell)^2 \mathbb{E} \left[\frac{1}{N} \mathbf{a}_k^H \mathbf{Q}_\ell \mathbf{D} \mathbf{Q}_\ell \mathbf{a}_k \right] \\ &+ \mathcal{O}(N^{-\frac{1}{2}}). \end{aligned}$$

Again due to the normalization $\frac{1}{N}$, we can show that it is possible to replace $\mathbf{Q}_\ell$ by $\mathbf{Q}$ in the second term, thus leading to:

$$\begin{aligned} & \mathbb{E} \left[\sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k \right] \\ &= \sum_{\ell \neq k} p_\ell \lambda^2 \tilde{t}_{\ell\ell}^2 \mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k] \\ &+ \sum_{\ell \neq k} \tilde{d}_\ell p_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \mathbb{E} \left[\frac{1}{N} \mathbf{a}_k^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_k \right] + \mathcal{O}(N^{-\frac{1}{2}}) \end{aligned}$$

or equivalently:

$$\sum_{\ell \neq k} p_\ell \lambda^2 \tilde{t}_{\ell\ell}^2 \mathbb{E} [\mathbf{a}_k^H \mathbf{Q}_\ell \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q}_\ell \mathbf{a}_k] \quad (185)$$

$$\begin{aligned} &= \mathbb{E} \left[\sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k \right] \\ &- \frac{1}{N} \sum_{\ell \neq k} \tilde{d}_\ell p_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_k] + \mathcal{O}(N^{-\frac{1}{2}}) \quad (186) \end{aligned}$$

which proves that:

$$\begin{aligned} \check{s}_{k,2} &= \sum_{\ell \neq k} p_\ell (1 + \tilde{d}_\ell \delta)^{-2} \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{a}_\ell \mathbf{a}_\ell^H \mathbf{Q} \mathbf{a}_k] \\ &+ \left(\frac{1}{N} \sum_{\ell \neq k} \lambda^2 \tilde{t}_{\ell\ell}^2 p_\ell \tilde{d}_\ell - \frac{1}{N} \sum_{\ell \neq k} \tilde{d}_\ell p_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \right) \\ &\times \mathbb{E} [\mathbf{a}_k^H \mathbf{Q} \mathbf{D} \mathbf{Q} \mathbf{a}_k] + \mathcal{O}(N^{-\frac{1}{2}}). \quad (187) \end{aligned}$$

Using Corollary 1 and Corollary 2, we obtain (188) on the top of next page. Plugging (184) and (188) into (176) yields (51).

A.2) Deterministic equivalent for ψ

To begin with, we apply Lemma 2 in Appendix C to $\psi = \frac{1}{K} \text{Tr} \mathbf{P} \boldsymbol{\Sigma}^H \mathbf{Q}^2 \boldsymbol{\Sigma}$. In doing so, we obtain:

$$\psi - \frac{1}{K} \sum_{k=1}^K p_k \mathbb{E} [\boldsymbol{\eta}_k^H \mathbf{Q}^2 \boldsymbol{\eta}_k] \xrightarrow{\text{a.s.}} 0. \quad (189)$$

Then, observe that (using the same calculus for s_k):

$$\frac{1}{K} \sum_{k=1}^K p_k \mathbb{E} [\boldsymbol{\eta}_k^H \mathbf{Q}^2 \boldsymbol{\eta}_k] \quad (190)$$

$$= \frac{1}{K} \sum_{\ell=1}^K p_\ell \lambda^2 (\tilde{t}_{\ell\ell})^2 \boldsymbol{\eta}_\ell^H \mathbf{Q}_\ell^2 \boldsymbol{\eta}_\ell + \mathcal{O}(N^{-\frac{1}{2}}) \quad (191)$$

$$= \frac{1}{K} \sum_{\ell=1}^K p_\ell \lambda^2 \tilde{t}_{\ell\ell}^2 \left[\tilde{d}_\ell \frac{1}{N} \text{Tr} \mathbf{E} \mathbf{D} \mathbf{Q}^2 + \mathbb{E} \mathbf{a}_\ell^H \mathbf{Q}_\ell^2 \mathbf{a}_\ell \right] + \mathcal{O}(N^{-\frac{1}{2}}) \quad (192)$$

$$\begin{aligned} &= \frac{1}{K} \sum_{\ell=1}^K \left[p_\ell \lambda^2 \tilde{t}_{\ell\ell}^2 \tilde{d}_\ell - p_\ell \tilde{d}_\ell \frac{(\mathbf{a}_\ell^H \mathbf{T} \mathbf{a}_\ell)^2}{(1 + \tilde{d}_\ell \delta)^4} \right] \mathbb{E} \left[\frac{1}{N} \text{Tr} \mathbf{D} \mathbf{Q}^2 \right] \\ &+ \frac{1}{K} \sum_{\ell=1}^K \frac{p_\ell}{(1 + \tilde{d}_\ell \delta)^2} \mathbb{E} [\mathbf{a}_\ell^H \mathbf{Q}^2 \mathbf{a}_\ell] + \mathcal{O}(N^{-\frac{1}{2}}). \quad (193) \end{aligned}$$

Using Theorem 1, we obtain (194) on the top of next page. From the relation $\mathbf{T} \mathbf{A} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-1} = (\mathbf{I}_N + \delta \tilde{\mathbf{D}})^{-1} \mathbf{A} \tilde{\mathbf{T}}$, it is easy to see that

$$\mathbf{V} = \frac{1}{N} \text{Tr} \tilde{\mathbf{D}} (\mathbf{I}_K + \delta \tilde{\mathbf{D}})^{-2} \mathbf{A}^H \mathbf{T}^2 \mathbf{A}. \quad (195)$$

Using (39), we finally obtain (after performing some simplifications) the sought-for result.

APPENDIX C

SOME ADDITIONAL USEFUL RESULTS

Lemma 1 (Trace Lemma). *Let $\mathbf{z} \in \mathbb{C}^N$ be a complex Gaussian vector with mean $\sqrt{N} \boldsymbol{\mu}$ and covariance matrix $\mathbf{I}_N$. Let $\mathbf{M}$ be a complex matrix independent of $\mathbf{z}$. Then, there exists a constant K_p such that:*

$$\begin{aligned} \mathbb{E}_{\mathbf{z}} \left| \frac{1}{N} \mathbf{z}^H \mathbf{M} \mathbf{z} - \frac{1}{N} \text{Tr} \mathbf{M} - \boldsymbol{\mu}^H \mathbf{M} \boldsymbol{\mu} \right|^p &\leq \frac{K_p}{N^p} \left((\text{Tr} \mathbf{M} \mathbf{M}^H)^{\frac{p}{2}} \right. \\ &\left. + N^{\frac{p}{2}} |\boldsymbol{\mu}^H \mathbf{M}^2 \boldsymbol{\mu}|^{\frac{p}{2}} \right). \quad (196) \end{aligned}$$

Lemma 2. *If $\mathbf{B} \in \mathbb{C}^{N \times N}$ is a sequence of deterministic matrices with uniformly bounded spectral norm, then*

$$\mathbb{E} \left| \frac{1}{K} \text{Tr} \mathbf{B} \mathbf{Q} \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H \mathbf{Q} - \mathbb{E} \left[\frac{1}{K} \text{Tr} \mathbf{B} \mathbf{Q} \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H \mathbf{Q} \right] \right|^4 = \mathcal{O}(N^{-4}). \quad (197)$$

If $\mathbf{u}$ is a sequence of deterministic vectors with bounded norm, then:

$$\mathbb{E} \left| \mathbf{u}^H \mathbf{Q} \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H \mathbf{Q} \mathbf{u} - \mathbb{E} [\mathbf{u}^H \mathbf{Q} \boldsymbol{\Sigma} \boldsymbol{\Sigma}^H \mathbf{Q} \mathbf{u}] \right|^6 = \mathcal{O}(N^{-3}). \quad (198)$$

Proof. The proof follows from the Nash-Poincaré inequality. Calculations are similar to the ones performed to prove Lemma 5 in [32]. Details are thus omitted. $\square$

$$\begin{aligned} \check{s}_{k,2} = & \lambda^2(1 + \delta\tilde{d}_k)^2[\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{kk} - \lambda^2\tilde{t}_{kk}^2(1 + \delta\tilde{d}_k)^2p_k + \left(\lambda^2(1 + \delta\tilde{d}_k)^2[\tilde{\mathbf{T}}\mathbf{D}\tilde{\mathbf{T}}]_{kk} - \lambda^2\tilde{t}_{kk}^2(1 + \delta\tilde{d}_k)^2\tilde{d}_k + (\mathbf{a}_k^H\mathbf{T}\mathbf{a}_k)^2\tilde{d}_k(1 + \delta\tilde{d}_k)^{-2}\right) \\ & \times \left(\frac{1-F}{\Delta}\frac{1}{N}\sum_{\ell=1}^K p_\ell\tilde{\gamma}_\ell + \frac{\vartheta}{\Delta}\frac{1}{N}\sum_{\ell=1}^K \lambda^2\tilde{d}_\ell[\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{\ell\ell}\right) + (1 + \delta\tilde{d}_k)^2\tilde{\gamma}_k \left(\frac{1-F}{\Delta}\frac{1}{N}\sum_{\ell=1}^K \tilde{d}_\ell[\tilde{\mathbf{T}}\mathbf{P}\tilde{\mathbf{T}}]_{\ell\ell} + \frac{\lambda^2\tilde{\vartheta}}{\Delta}\frac{1}{N}\sum_{\ell=1}^K p_\ell\tilde{\gamma}_\ell\right) + \mathcal{O}(N^{-\frac{1}{2}}). \end{aligned} \quad (188)$$

$$\begin{aligned} \psi = & \left(\frac{1}{K}\sum_{l=1}^K p_l\lambda^2\tilde{t}_{ll}^2\tilde{d}_l - p_l\tilde{d}_l\frac{(\mathbf{a}_l^H\mathbf{T}\mathbf{a}_l)^2}{(1 + \tilde{d}_l\delta)^4}\right) \left(\frac{1-F}{\Delta}\frac{1}{N}\text{Tr}\mathbf{D}\mathbf{T}^2 + \frac{\vartheta}{\Delta}\frac{1}{N}\text{Tr}\tilde{\mathbf{D}}(\mathbf{I}_K + \delta\tilde{\mathbf{D}})^{-2}\mathbf{A}^H\mathbf{T}^2\mathbf{A}\right) \\ & + \frac{1}{K}\sum_{l=1}^K \frac{p_l}{(1 + \tilde{d}_l\delta)^2} \left[\mathbf{a}_l^H\mathbf{T}\mathbf{A}\tilde{\mathbf{D}}(\mathbf{I}_K + \delta\tilde{\mathbf{D}})^{-2}\mathbf{A}^H\mathbf{T}\mathbf{a}_l \left(\frac{1-F}{\Delta}\frac{1}{N}\text{Tr}\mathbf{D}\mathbf{T}^2 + \frac{\vartheta}{\Delta}\frac{1}{N}\text{Tr}\tilde{\mathbf{D}}(\mathbf{I}_K + \delta\tilde{\mathbf{D}})^{-2}\mathbf{A}^H\mathbf{T}^2\mathbf{A}\right) \right. \\ & \left. + \mathbf{a}_l^H\mathbf{T}^2\mathbf{a}_l + \mathbf{a}_l^H\mathbf{T}\mathbf{D}\mathbf{T}\mathbf{a}_l \left(\frac{1}{N}\text{Tr}\tilde{\mathbf{D}}(\mathbf{I}_K + \delta\tilde{\mathbf{D}})^{-2}\mathbf{A}^H\mathbf{T}^2\mathbf{A} + \frac{\lambda^2\tilde{\vartheta}}{\Delta}\frac{1}{N}\text{Tr}\mathbf{D}\mathbf{T}^2\right)\right] + \mathcal{O}(N^{-\frac{1}{2}}). \end{aligned} \quad (194)$$

REFERENCES

- [1] T. Marzetta, "Noncooperative cellular wireless with unlimited numbers of base station antennas," *IEEE Transactions on Wireless Communications*, vol. 9, no. 11, pp. 3590 – 3600, Nov. 2010.
- [2] F. Rusek, D. Persson, B. K. Lau, E. Larsson, T. Marzetta, O. Edfors, and F. Tufvesson, "Scaling up MIMO: Opportunities and challenges with very large arrays," *IEEE Signal Processing Magazine*, vol. 30, no. 1, pp. 40 – 60, Jan 2013.
- [3] E. Larsson, O. Edfors, F. Tufvesson, and T. Marzetta, "Massive MIMO for next generation wireless systems," *IEEE Communications Magazine*, vol. 52, no. 2, pp. 186 – 195, February 2014.
- [4] E. Björnson, J. Hoydis, and L. Sanguinetti, "Massive MIMO has unlimited capacity," *IEEE Transactions on Wireless Communications*, vol. PP, no. 99, pp. 1–1, 2017.
- [5] H. Ngo, E. Larsson, and T. Marzetta, "Energy and spectral efficiency of very large multiuser MIMO systems," *IEEE Trans. Commun.*, vol. 61, no. 4, pp. 1436–1449, 2013.
- [6] E. Björnson, L. Sanguinetti, J. Hoydis, and M. Debbah, "Optimal design of energy-efficient multi-user MIMO systems: Is massive MIMO the answer?" *IEEE Trans. Wireless Commun.*, vol. 14, no. 6, pp. 3059–3075, 2015.
- [7] E. Björnson, L. Sanguinetti, and M. Kountouris, "Deploying dense networks for maximal energy efficiency: Small cells meet massive MIMO," *EEE Journal on Selected Areas in Communications*, 2016. [Online]. Available: <http://arxiv.org/pdf/1505.01181.pdf>
- [8] S. Wagner, R. Couillet, M. Debbah, and D. T. M. Slock, "Large system analysis of linear precoding in correlated MISO broadcast channels under limited feedback," *IEEE Trans. Inf. Theory*, vol. 58, no. 7, pp. 4509–4537, July 2012.
- [9] J. Hoydis, S. ten Brink, and M. Debbah, "Massive MIMO in the UL/DL of cellular networks: How many antennas do we need?" *IEEE J. Sel. Areas Commun.*, vol. 31, no. 2, pp. 160 – 171, Feb. 2013.
- [10] L. Sanguinetti, R. Couillet, and M. Debbah, "Large system analysis of base station cooperation in the downlink," *IEEE Trans. Wireless Commun.*, 2015, under review. [Online]. Available: <http://arxiv.org/pdf/1509.00731v1.pdf>
- [11] J. Zhang, C.-K. Wen, S. Jin, X. Gao, and K.-K. Wong, "Large system analysis of cooperative multi-cell downlink transmission via regularized channel inversion with imperfect CSIT," *IEEE Trans. Wireless Commun.*, vol. 12, no. 10, October 2013.
- [12] R. Couillet and M. Debbah, *Random matrix methods for wireless communications*. Cambridge, New York: Cambridge University Press, 2011.
- [13] W. Hachem, M. Kharouf, J. Najim, and J. W. Silverstein, "A CLT for information-theoretic statistics of non-centered Gram random matrices," *Random Matrices: Theory and Applications*, vol. 1, no. 2, pp. 1–50, 2012. [Online]. Available: <https://hal.archives-ouvertes.fr/hal-00829214>
- [14] W. Hachem, P. Loubaton, J. Najim, and P. Vallet, "On bilinear forms based on the resolvent of large random matrices," *Annales de l'Institut Henri Poincaré, Probabilités et Statistiques*, vol. 49, no. 1, pp. 36 – 63, 2013.
- [15] D. Yue and G. Y. Li, "LOS-based conjugate beamforming and power-scaling law in massive-MIMO systems," *CoRR*, vol. abs/1404.1654, 2014. [Online]. Available: <http://arxiv.org/abs/1404.1654>
- [16] J. Hoydis, A. Kammoun, J. Najim, and M. Debbah, "Outage performance of cooperative small-cell systems under Rician fading channels," in *IEEE 12th International Workshop on Signal Processing Advances in Wireless Communications (SPAWC)*, June 2011, pp. 551–555.
- [17] J. Zhang, C.-K. Wen, S. Jin, X. Gao, and K.-K. Wong, "On capacity of large-scale MIMO multiple access channels with distributed sets of correlated antennas," *IEEE J. Sel. Areas Commun.*, vol. 31, no. 2, pp. 133 – 148, February 2013.
- [18] Q. Zhang, S. Jin, K.-K. Wong, H. Zhu, and M. Matthaiou, "Power scaling of uplink massive MIMO systems with arbitrary-rank channel means," *IEEE J. Sel. Topics Signal Process.*, vol. 8, no. 5, pp. 966 – 981, Oct 2014.
- [19] Q. Zhang, S. Jin, K. K. Wong, H. Zhu, and M. Matthaiou, "Power scaling of uplink massive MIMO systems with arbitrary-rank channel means," *IEEE J. Sel. Topics Signal Process.*, vol. 8, no. 5, pp. 966–981, Oct 2014.
- [20] H. AL-Salihi and F. Said, "Performance evaluation of Massive MIMO in correlated Rician and correlated Nakagami-m fading," in *2015 9th International Conference on Next Generation Mobile Applications, Services and Technologies*, Sept 2015, pp. 222–227.
- [21] Y. Huang, S. Ma, and Y. Wang, "Uplink achievable rate of full-duplex multi-cell massive MIMO systems," in *2015 IEEE International Conference on Communication Workshop (ICCW)*, June 2015, pp. 1131–1136.
- [22] J. Zhang, L. Dai, X. Zhang, E. Björnson, and Z. Wang, "Achievable rate of Rician large-scale MIMO channels with transceiver hardware impairments," *IEEE Transactions on Vehicular Technology*, vol. 65, no. 10, pp. 8800–8806, Oct 2016.
- [23] A. Adhikary, J. Nam, J.-Y. Ahn, and G. Caire, "Joint spatial division and multiplexing – the large-scale array regime," *IEEE Trans. Inf. Theory*, vol. 59, no. 10, pp. 6441–6463, Oct 2013.
- [24] A. Kammoun, A. Muller, E. Björnson, and M. Debbah, "Linear precoding based on polynomial expansion: Large-scale multi-cell MIMO systems," *IEEE J. Sel. Topics Signal Process.*, vol. 8, no. 5, pp. 861–875, Oct 2014.
- [25] J. Nam, A. Adhikary, J. Y. Ahn, and G. Caire, "Joint spatial division and multiplexing: Opportunistic beamforming, user grouping and simplified downlink scheduling," *IEEE Journal of Selected Topics in Signal Processing*, vol. 8, no. 5, pp. 876–890, Oct 2014.
- [26] A. Kammoun, M. Kharouf, W. Hachem, and J. Najim, "A central limit theorem for the sinr at the lmmse estimator output for large-dimensional signals," *IEEE Transactions on Information Theory*, vol. 55, no. 11, pp. 5048 – 5063, nov. 2009.
- [27] E. Björnson, J. Hoydis, and L. Sanguinetti, "Massive MIMO networks: Spectral, energy, and hardware efficiency," *Foundations and Trends in Signal Processing*, vol. 11, no. 3-4, pp. 154–655, 2017. [Online]. Available: <http://dx.doi.org/10.1561/20000000093>
- [28] H. Q. Ngo, E. G. Larsson, and T. L. Marzetta, "Aspects of favorable

propagation in massive MIMO,” in *Proceedings of the 22nd European Signal Processing Conference (EUSIPCO)*, Sept 2014, pp. 76–80.

- [29] E. Björnson, E. G. Larsson, and T. L. Marzetta, “Massive MIMO: ten myths and one critical question,” *IEEE Commun. Mag.*, vol. 54, no. 2, pp. 114–123, February 2016.
- [30] L. Sanguinetti, A. L. Moustakas, E. Björnson, and M. Debbah, “Large system analysis of the energy consumption distribution in multi-user MIMO systems with mobility,” *IEEE Transactions on Wireless Communications*, vol. 14, no. 3, pp. 1730 – 1745, March 2015.
- [31] R. A. Horn and C. R. Johnson, *Matrix Analysis*, 2nd ed. New York, NY, USA: Cambridge University Press, 2012.
- [32] C. Artigue and P. Loubaton, “On the Precoder Design of Flat Fading MIMO Systems Equipped With MMSE Receivers: A Large System Approach,” *IEEE Trans. Inf. Theory*, vol. 57, no. 7, 2011.

Abla Kammoun (S’06, M’10) was born in Sfax, Tunisia. She received the engineering degree in signal and systems from the Tunisia Polytechnic School, La Marsa, and the Master and the Ph.D. degrees in digital communications from Télécom Paris Tech [then Ecole Nationale Supérieure des Télécommunications (ENST)]. From June 2010 to April 2012, she has been a Postdoctoral Researcher in the TSI Department, Télécom Paris Tech. Then she was with the Alcatel-Lucent Chair on Flexible Radio at CentraleSupélec, Gif-sur-Yvette, France from May 2012 to October 2013. She joined KAUST university in 2014 where she is currently working as a research scientist. Her research interests include asymptotic performance analysis, random matrix theory and statistical signal processing. She is the co-recipient of the SAM 2014 second Prize Best paper award.

Luca Sanguinetti (SM’15) received the Laurea Telecommunications Engineer degree (cum laude) and the Ph.D. degree in information engineering from the University of Pisa, Italy, in 2002 and 2005, respectively. In 2004, he was a visiting Ph.D. student at the German Aerospace Center (DLR), Oberpfaffenhofen, Germany. During the period June 2007 - June 2008, he was a postdoctoral associate in the Dept. Electrical Engineering at Princeton. From July 2013 to October 2017 he was with Large Systems and Networks Group (LANEAS), CentraleSupélec,

France. He is currently an Associate Professor in the ‘Dipartimento di Ingegneria dell’Informazione’ of the University of Pisa, Italy.

He served as an Associate Editor for IEEE TRANSACTIONS ON WIRELESS COMMUNICATIONS, and as Lead Guest Editor of IEEE JOURNAL ON SELECTED AREAS OF COMMUNICATIONS Special Issue on “Game Theory for Networks” and as an Associate Editor for IEEE JOURNAL ON SELECTED AREAS OF COMMUNICATIONS (series on Green Communications and Networking). Dr. Sanguinetti is currently serving as an Associate Editor for the IEEE SIGNAL PROCESSING LETTERS, IEEE TRANSACTIONS ON COMMUNICATIONS and is a member of the Executive Editorial Committee of IEEE TRANSACTIONS ON WIRELESS COMMUNICATIONS.

His expertise and general interests span the areas of communications and signal processing. Dr. Sanguinetti has co-authored the textbook *Massive MIMO Networks: Spectral, Energy, and Hardware Efficiency* (2017). He received the 2018 Marconi Prize Paper Award in Wireless Communications and co-authored a paper that received the young best paper award from the ComSoc/VTS Italy Section. He was the co-recipient of two best conference paper awards: *IEEE WCNC 2013* and *IEEE WCNC 2014*. He was the recipient of the FP7 Marie Curie IEF 2013 “Dense deployments for green cellular networks”.

M'rouane Debbah (S01M04SM08F15) received the M.Sc. and Ph.D. degrees from the Ecole Normale Supérieure Paris-Saclay, France. In 1996, he joined the Ecole Normale Supérieure Paris-Saclay. He was with Motorola Labs, Saclay, France, from 1999 to 2002, and also with the Vienna Research Center for Telecommunications, Vienna, Austria, until 2003. From 2003 to 2007, he was an Assistant Professor with the Mobile Communications Department, Institut Eurecom, Sophia Antipolis, France. From 2007 to 2014, he was the Director of the Alcatel-Lucent Chair on Flexible Radio. Since 2007, he has been a Full Professor with CentraleSupélec, Gif-sur-Yvette, France. Since 2014, he has been a Vice-President of the Huawei France Research Center and the Director of the Mathematical and Algorithmic Sciences Lab. He has managed 8 EU projects and more than 24 national and international projects. His research interests lie in fundamental mathematics, algorithms, statistics, information, and communication sciences research. He is an IEEE Fellow, a WWRF Fellow, and a Membre émérite SEE. He was a recipient of the ERC Grant MORE (Advanced Mathematical Tools for Complex Network Engineering) from 2012 to 2017. He was a recipient of the Mario Boella Award in 2005, the IEEE Glavieux Prize Award in 2011, and the Qualcomm Innovation Prize Award in 2012. He received 20 best paper awards, among which the 2007 IEEE GLOBECOM Best Paper Award, the Wi-Opt 2009 Best Paper Award, the 2010 Newcom++ Best Paper Award, the WUN CogCom Best Paper 2012 and 2013 Award, the 2014 WCNC Best Paper Award, the 2015 ICC Best Paper Award, the 2015 IEEE Communications Society Leonard G. Abraham Prize, the 2015 IEEE Communications Society Fred W. Ellersick Prize, the 2016 IEEE Communications Society Best Tutorial Paper Award, the 2016 European Wireless Best Paper Award, the 2017 Eurasp Best Paper Award, the 2018 IEEE Marconi Prize Paper Award, the 2019 IEEE Communications Society Young Author Best Paper Award and the Valuetools 2007, Valuetools 2008, CrownCom 2009, Valuetools 2012, SAM 2014, and 2017 IEEE Sweden VT-COM-IT Joint Chapter best student paper awards. He is an Associate Editor-in-Chief of the journal Random Matrix: Theory and Applications. He was an Associate Area Editor and Senior Area Editor of the IEEE TRANSACTIONS ON SIGNAL PROCESSING from 2011 to 2013 and from 2013 to 2014, respectively.

Mohamed-Slim Alouini (S94M98SM03F09) was born in Tunis, Tunisia. He received the Ph.D. degree in electrical engineering from the California Institute of Technology, Pasadena, CA, USA, in 1998. He served as a faculty member with the University of Minnesota, Minneapolis, MN, USA, then with the Texas A&M University at Qatar, Education City, Doha, Qatar, before joining the King Abdullah University of Science and Technology, Thuwal, Makkah, Saudi Arabia, as a Professor of electrical engineering in 2009. His current research interests include

the modeling, design, and performance analysis of wireless communication systems.